



# Topological entropy of switched nonlinear and interconnected systems

Guosong Yang<sup>1</sup> · Daniel Liberzon<sup>2</sup> · João P. Hespanha<sup>3</sup>

Received: 16 May 2022 / Accepted: 31 January 2023 / Published online: 2 April 2023

© The Author(s), under exclusive licence to Springer-Verlag London Ltd., part of Springer Nature 2023

## Abstract

A general upper bound for topological entropy of switched nonlinear systems is constructed, using an asymptotic average of upper limits of the matrix measures of Jacobian matrices of strongly persistent individual modes, weighted by their active rates. A general lower bound is constructed as well, using a similar weighted average of lower limits of the traces of these Jacobian matrices. In a case of interconnected structure, the general upper bound is readily applied to derive upper bounds for entropy that depend only on “network-level” information. In a case of block-diagonal structure, less conservative upper and lower bounds for entropy are constructed. In each case, upper bounds for entropy that require less information about the switching signal are also derived. The upper bounds for entropy and their relations are illustrated by numerical examples of a switched Lotka–Volterra ecosystem model.

**Keywords** Topological entropy · Switched systems · Nonlinear systems · Interconnected systems

---

This paper is dedicated to Prof. Eduardo D. Sontag on the occasion of his 70th birthday. As detailed later in the paper, our work is heavily influenced by Prof. Sontag’s research contributions to the areas of contractive nonlinear and interconnected systems.

---

✉ Guosong Yang  
guosong.yang@rutgers.edu

Daniel Liberzon  
liberzon@illinois.edu

João P. Hespanha  
hespanha@ucsb.edu

<sup>1</sup> Department of Electrical and Computer Engineering, Rutgers University-New Brunswick, Piscataway, NJ 08854, USA

<sup>2</sup> Coordinated Science Laboratory, University of Illinois Urbana-Champaign, Urbana, IL 61801, USA

<sup>3</sup> Center for Control, Dynamical Systems, and Computation, University of California, Santa Barbara, Santa Barbara, CA 93106, USA

## 1 Introduction

Topological entropy is a fundamental concept in dynamical systems theory. Roughly speaking, it describes the rate at which uncertainty about the state of a system grows as time evolves. More concretely, one can think of it as the exponential growth rate of the number of trajectories that are separable with a finite precision, or in terms of the exponential growth rate of the size of the reachable set. Adler et al. first defined topological entropy as an extension to Kolmogorov's metric entropy [21], quantifying the expansion of a function using the minimal cardinality of a subcover refinement [1]. A different definition using the number of separable trajectories was later proposed by Bowen [7] and independently by Dinaburg [15]. An equivalence between these two definitions was established in [8]. Most existing results on this topic considered only time-invariant systems, as time-varying dynamics introduce complexities that require new methods to understand [20, 22]. The results on topological entropy of switched systems in the current paper contributes to the understanding of these complexities.

Entropy notions also play a prominent role in control theory. The first such result was a notion of topological feedback entropy for discrete-time systems defined by Nair et al. [35], which extended the formulation in [1] and described the growth rate of control complexity for achieving set invariance. A notion of invariance entropy for continuous-time systems was later introduced by Colonius and Kawan [12], which was closer in concept to the trajectory-counting formulation in [7, 15]. An equivalence between these two definitions was established in [13]. Entropy notions were also proposed for stabilization [11], state estimation [28, 32, 37], and model detection [28].

In this paper, we study topological entropy of continuous-time switched nonlinear systems. Switched systems have been a popular topic in recent years (see, e.g., [23, 38] and references therein). In general, a switched system does not inherit stability properties of its individual modes. For example, a switched linear system with two stable modes may still be unstable (see, e.g., [23, p. 19]). On the other hand, it is well known that a switched linear system generated by a finite family of pairwise commuting Hurwitz matrices is globally exponentially stable under arbitrary switching (see, e.g., [23, Th. 2.5, p. 31]). This result has been extended to global uniform asymptotic stability for switching nonlinear systems with pairwise commuting, globally asymptotically stable modes [31, 45]. A simplest case of pairwise commuting modes is when the modes are simultaneously diagonalizable, which motivates us to consider cases with diagonal and block-diagonal structures in addition to the general case.

We are also interested in switched systems with interconnected structures. In systems and control theory, it is a tremendously important paradigm to represent a large complex system as an interconnection of smaller and simpler subsystems, and establish properties of the overall system by analyzing its individual components. A classical example of this paradigm is the use of small-gain theorems for establishing stability of interconnected linear, nonlinear, and switched systems (see, e.g., [14, 29, 46]).

Our interest in topological entropy of switched systems is strongly motivated by its relations to data rate requirements in control problems. For a continuous-time linear time-invariant control system, the minimal data rate for feedback stabilization is given by the sum of the positive real parts of eigenvalues of the system matrix [16] (or, in the discrete-time case, the sum of their logarithms [16, 34, 41]), which is equal to the

topological entropy in open loop [7, 12]. Data rate requirements and entropy notions for nonlinear and interconnected time-invariant control systems have been extensively studied (see, e.g., [11, 19, 27, 33, 35, 42]). For switched systems, however, neither data rate requirements in control problems nor topological entropy are completely understood. Sufficient data rates for feedback stabilization of switched linear systems were established in [25, 47]. Similar data rate conditions were constructed in [39] by extending a notion of estimation entropy from [28]. In [48, 50], formulae and bounds for topological entropy of switched linear systems were constructed using the active rates of individual modes, an approach that is also adopted in the current paper. Relations between topological entropy and stability of switched linear systems were studied in [49, 50]. For discrete-time switched linear systems, the topological entropy under worst-case switching sequences was obtained based on the notion of joint spectral radius [4], while a formula for estimation entropy was constructed under additional regularity conditions [43].

For switched nonlinear systems, topological entropy has not been closely explored so far. The main objective of this paper is to construct upper and lower bounds for topological entropy of switched nonlinear systems with general and interconnected structures. We start by introducing in Sect. 2 the necessary preliminaries to understand our bounds for entropy, including the definitions of topological entropy for switched systems, and some switching-related quantities such as the active rates of individual modes, and persistent and strongly persistent modes.

In Sect. 3, we construct a general upper bound for topological entropy of switched nonlinear systems, using an asymptotic average of upper limits of the matrix measures of Jacobian matrices of strongly persistent modes, weighted by their active rates. A general lower bound is constructed as well, using a similar weighted average of lower limits of the traces of these Jacobian matrices. These bounds, as well as all bounds for entropy in this paper, depend on the values of Jacobian matrices of only the strongly persistent modes and over only an  $\omega$ -limit set. Moreover, the bounds constructed using matrix measures hold regardless of the induced norm with which the matrix measures are computed, as long as the same one is used for all modes.

In Sect. 4, we consider switched systems with interconnected structures. We show in Sect. 4.1 that the general upper bound from Sect. 3 can be readily applied to derive upper bounds for entropy of switched interconnected systems that depend only on “network-level” information. In Sect. 4.2, we consider an interconnected case where the dynamics of subsystems are independent (i.e., a case of block-diagonal structure), and construct less conservative upper and lower bounds for entropy. The upper and lower bounds for entropy from Sect. 3 can be seen as a special case of the bounds here, as any switched system can be seen as a switched block-diagonal system with a single block.

In each general and interconnected case, we also derive in the corresponding section upper bounds for entropy that are more conservative but require less information about the switching signal, with their relations illustrated by numerical examples of a switched Lotka–Volterra ecosystem model in Sect. 5. The main proofs, along with the necessary technical preliminaries, are presented in Sect. 6. Section 7 concludes the paper with a brief summary and some remarks on future research directions.

A preliminary version of some of the results in current paper was presented in the paper [51]. The current paper improves upon [51] by introducing persistent and strongly persistent modes, considering cases with interconnected and block-diagonal structures, and providing more extensive numerical examples, analysis details, and explanatory remarks.

*Notations:* Denote by  $\mathbf{1}_n$  the vector of ones in  $\mathbb{R}^n$ , and by  $I_n$  and  $\mathbf{1}_{n \times n}$  the identity matrix and matrix of ones in  $\mathbb{R}^{n \times n}$ , respectively; the subscript is omitted when the dimension is clear from context. For a complex number  $c$ , denote by  $\operatorname{Re}(c)$  its real part. For  $k \geq 2$  vectors  $v_1 \in \mathbb{R}^{n_1}, \dots, v_k \in \mathbb{R}^{n_k}$ , denote by  $(v_1, \dots, v_k) := [v_1^\top \dots v_k^\top]^\top \in \mathbb{R}^{n_1 + \dots + n_k}$  their concatenation. For a matrix  $A \in \mathbb{R}^{n \times n}$ , denote by  $\operatorname{tr}(A)$ ,  $\det(A)$ , and  $\operatorname{spec}(A)$  its trace, determinant, and spectrum (as a multiset in which each eigenvalue has a number of instances equal to its algebraic multiplicity), respectively. For a finite set  $E$ , denote by  $\#E$  its cardinality. For a set  $S \subset \mathbb{R}^n$ , denote by  $\operatorname{co}(S)$  and  $\operatorname{vol}(S)$  its convex hull and volume (Lebesgue measure), respectively. Denote by  $\|v\|_\infty := \max_{1 \leq i \leq n} |v_i|$  the  $\infty$ -norm of a vector  $v = (v_1, \dots, v_n) \in \mathbb{R}^n$ , and by  $\|A\|_\infty = \max_{1 \leq i \leq n} \sum_{j=1}^n |a_{ij}|$  the induced  $\infty$ -norm of a matrix  $A = [a_{ij}] \in \mathbb{R}^{n \times n}$ . By default, all logarithms are natural logarithms (in order to avoid generating an extra multiplicative factor  $\ln 2$  when computing topological entropy).

## 2 Preliminaries

Consider a *finite* family of continuous-time nonlinear dynamical systems

$$\dot{x} = f_p(x), \quad p \in \mathcal{P} \quad (1)$$

with state  $x \in \mathbb{R}^n$ , in which each system is labeled with an index  $p$ , and  $\mathcal{P}$  is the corresponding finite set of indices. We assume that the functions  $f_p$  are continuously differentiable, and the systems in (1) are forward complete. We are interested in the corresponding *switched system* defined by

$$\dot{x} = f_\sigma(x) \quad (2)$$

with a right-continuous, piecewise-constant *switching signal*  $\sigma : \mathbb{R}_{\geq 0} \rightarrow \mathcal{P}$ . We call the system with index  $p$  in (1) *mode  $p$*  of the switched system (2), and  $\sigma(t)$  the *active mode* at time  $t$ . We denote by  $\xi_\sigma(t, x)$  the solution to (2) with switching signal  $\sigma$  at time  $t \geq 0$  with initial state  $x$  (at time 0). Under the above assumptions,  $\xi_\sigma(t, x)$  is unique, absolutely continuous in  $t$ , continuously differentiable in  $x$ , and satisfies the differential equation (2) away from discontinuities of  $\sigma$ , which are called *switching times*, or simply *switches*. We assume that there is at most one switch at each time, and finitely many switches in each finite time interval (i.e., the set of switches contains no accumulation point). For brevity, we denote by

$$J_x f_p(v) := J_x f_p(x)|_{x=v}, \quad J_x \xi_\sigma(t, v) := J_x \xi_\sigma(t, x)|_{x=v}$$

the Jacobian matrix of function  $f_p(x)$  in mode  $p$  of (2) at state  $x = v$ , and that of solution  $\xi_\sigma(t, x)$  to (2) with respect to initial state  $x$  at time  $t$  and  $x = v$ , respectively.

## 2.1 Entropy definitions

We now define the topological entropy of the switched system (2) with switching signal  $\sigma$  and initial states drawn from a compact set with nonempty interior  $K \subset \mathbb{R}^n$  called the *initial set*. Let  $|\cdot|$  be a norm on  $\mathbb{R}^n$  and  $\|\cdot\|$  the corresponding induced norm on  $\mathbb{R}^{n \times n}$ . Given a time horizon  $T \geq 0$  and a radius  $\varepsilon > 0$ , we define the following open ball in  $\mathbb{R}^n$  with center  $x$ :

$$B_{f_\sigma}(x, \varepsilon, T) := \left\{ \bar{x} \in \mathbb{R}^n : \max_{t \in [0, T]} |\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| < \varepsilon \right\}. \quad (3)$$

We say that a finite set  $E \subset K$  is  $(T, \varepsilon)$ -spanning if

$$K \subset \bigcup_{x \in E} B_{f_\sigma}(x, \varepsilon, T), \quad (4)$$

or equivalently, for each  $\bar{x} \in K$ , there exists an  $x \in E$  such that  $|\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| < \varepsilon$  for all  $t \in [0, T]$ . We denote by  $S(f_\sigma, \varepsilon, T, K) \geq 1$  the minimal cardinality of a  $(T, \varepsilon)$ -spanning set, or equivalently, the cardinality of a minimal  $(T, \varepsilon)$ -spanning set, which is nondecreasing in  $T$  and nonincreasing in  $\varepsilon$ . The *topological entropy* of the switched system (2) with switching signal  $\sigma$  and initial set  $K$  is defined in terms of the exponential growth rate of  $S(f_\sigma, \varepsilon, T, K)$  by

$$h(f_\sigma, K) := \lim_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{1}{T} \log S(f_\sigma, \varepsilon, T, K) \geq 0. \quad (5)$$

For brevity, we at times refer to  $h(f_\sigma, K)$  simply as the (topological) entropy of (2).

**Remark 1** In view of the equivalence of norms on a finite-dimensional vector space, the value of  $h(f_\sigma, K)$  is the same for every norm  $|\cdot|$  on  $\mathbb{R}^n$ . In particular, it is invariant under a change of basis. (More generally, one can define topological entropy on a metric space  $(X, d)$  instead of the normed space  $(\mathbb{R}^n, |\cdot|)$ , in which case its value depends on the given metric, but is a topological invariant for an initial set contained in a compact positively invariant set; see [18, Prop. 3.1.2, p. 109] and [12, p. 1703] for more details.)

We also provide an alternative definition for the entropy of (2). For  $T \geq 0$  and  $\varepsilon > 0$  given as before, we say that a finite set  $E \subset K$  is  $(T, \varepsilon)$ -separated if

$$\bar{x} \notin B_{f_\sigma}(x, \varepsilon, T) \quad \forall x, \bar{x} \in E : \bar{x} \neq x, \quad (6)$$

or equivalently, for each pair of distinct  $x, \bar{x} \in E$ , there exists a time  $t \in [0, T]$  such that  $|\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| \geq \varepsilon$ . We denote by  $N(f_\sigma, \varepsilon, T, K) \geq 1$  the maximal cardinality of a  $(T, \varepsilon)$ -separated set, or equivalently, the cardinality of a maximal

$(T, \varepsilon)$ -separated set, which is also nondecreasing in  $T$  and nonincreasing in  $\varepsilon$ . As stated in the following result, the entropy of (2) can be equivalently defined in terms of the exponential growth rate of  $N(f_\sigma, \varepsilon, T, K)$ ; the proof is along the lines of [18, p. 110] and thus omitted here.

**Lemma 1** *The topological entropy of the switched system (2) satisfies*

$$h(f_\sigma, K) = \lim_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{1}{T} \log N(f_\sigma, \varepsilon, T, K). \quad (7)$$

**Remark 2** Following [18, pp. 109–110], for a time-invariant system  $\dot{x} = f(x)$  and an initial set  $K$  contained in a compact positively invariant set, the value of  $h(f, K)$  remains the same when the upper limits in (5) and (7) are replaced with lower limits. However, this is not necessarily true for the switched system (2), since the subadditivity required in the proof of [18, Lemma 3.1.5, p. 109] may not hold.

## 2.2 Active times, active rates, and persistent modes

Here we introduce some switching-related quantities that will be useful for constructing bounds for the topological entropy of the switched system (2). Given a switching signal  $\sigma$ , we define the *active time* of mode  $p$  of (2) over interval  $[0, t]$  by

$$\tau_p(t) := \int_0^t \mathbb{1}_p(\sigma(s)) ds, \quad p \in \mathcal{P} \quad (8)$$

with the indicator function

$$\mathbb{1}_p(\sigma(s)) := \begin{cases} 1, & \sigma(s) = p, \\ 0, & \sigma(s) \neq p. \end{cases}$$

We also define the *active rate* of mode  $p$  over  $[0, t]$  by

$$\rho_p(t) := \frac{\tau_p(t)}{t}, \quad p \in \mathcal{P} \quad (9)$$

with  $\rho_p(0) := \mathbb{1}_p(\sigma(0))$ , and the *asymptotic active rate* of mode  $p$  by

$$\hat{\rho}_p := \limsup_{t \rightarrow \infty} \rho_p(t), \quad p \in \mathcal{P}. \quad (10)$$

Clearly, the active times  $\tau_p(t) \geq 0$  are nondecreasing and satisfy  $\sum_{p \in \mathcal{P}} \tau_p(t) = t$  for all  $t \geq 0$ ; the active rates  $\rho_p(t) \in [0, 1]$  satisfy  $\sum_{p \in \mathcal{P}} \rho_p(t) = 1$  for all  $t \geq 0$ . In contrast, due to the upper limit in (10), it is possible that  $\sum_{p \in \mathcal{P}} \hat{\rho}_p > 1$  for the asymptotic active rates  $\hat{\rho}_p \geq 0$  (for a numerical example, see [50, Example 1]). Moreover, we define

$$\mathcal{P}_\infty := \{p \in \mathcal{P} : \sup\{t \geq 0 : \sigma(t) = p\} = \infty\}, \quad \mathcal{P}_\infty^+ := \{p \in \mathcal{P} : \hat{\rho}_p > 0\}, \quad (11)$$

and call them the sets of *persistent* and *strongly persistent* modes, respectively. Clearly, they satisfy  $\mathcal{P}_\infty^+ \subset \mathcal{P}_\infty$ .

### 3 Entropy of general switched nonlinear systems

In this section, we construct general upper and lower bounds for the topological entropy of the switched system (2). The upper bounds will be constructed based on a notion of matrix measure. For an induced norm  $\|\cdot\|$  on  $\mathbb{R}^{n \times n}$ , its one-sided directional derivative at  $I$  in direction  $A \in \mathbb{R}^{n \times n}$  is called the *matrix measure* of  $A$  and denoted by  $\mu(A)$ , that is,

$$\mu(A) := \lim_{t \searrow 0} \frac{\|I + tA\| - 1}{t}. \quad (12)$$

The matrix measure  $\mu(A)$  can also be seen as the right derivative of the functions  $t \mapsto \|e^{At}\|$  and  $t \mapsto \log \|e^{tA}\|$  at  $t = 0$  [5, Fact 11.15.7, p. 690]. A summary of properties of matrix measure can be found in [14, Th. 2.8.5, p. 31]. In particular,  $\mu$  is a convex function and satisfies

$$-\mu(-A) \leq \operatorname{Re}(\lambda) \leq \mu(A) \leq \|A\| \quad \forall A \in \mathbb{R}^{n \times n}, \lambda \in \operatorname{spec}(A) \quad (13)$$

and

$$\mu(A + B) \leq \mu(A) + \mu(B), \quad \mu(cA) = c\mu(A) \quad \forall A, B \in \mathbb{R}^{n \times n}, c \geq 0. \quad (14)$$

For standard induced norms, there are explicit formulae for the matrix measure [14, Th. 2.8.24, p. 33]; for example, for the induced  $\infty$ -norm, the matrix measure of  $A = [a_{ij}]$  is given by

$$\mu(A) = \max_{1 \leq i \leq n} \left( a_{ii} + \sum_{j \neq i} |a_{ij}| \right). \quad (15)$$

We denote by  $\xi_\sigma(t, K) := \{\xi_\sigma(t, x) : x \in K\}$  the *reachable set* of (2) with switching signal  $\sigma$  at time  $t$  from initial set  $K$ .

The following result provides upper and lower bounds for the entropy of (2); they are derived based on later results in this paper, which will be explained in the proof in Sect. 6.6.

**Theorem 1** *Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11).*

1. *Let*

$$\hat{\mu}_p := \limsup_{t \rightarrow \infty: \sigma(t) = p} \max_{v \in \xi_\sigma(t, \operatorname{co}(K))} \mu(J_x f_p(v)), \quad p \in \mathcal{P}. \quad (16)$$

If the constants  $\hat{\mu}_p$  are finite for all  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched system (2) is upper bounded by

$$h(f_\sigma, K) \leq \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} n \hat{\mu}_p \rho_p(t), 0 \right\}. \quad (17)$$

2. Let

$$\check{\chi}_p := \liminf_{t \rightarrow \infty: \sigma(t)=p} \min_{v \in \xi_\sigma(t, K)} \text{tr}(J_x f_p(v)), \quad p \in \mathcal{P}. \quad (18)$$

If the constants  $\check{\mu}_p$  are finite for all  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched system (2) is lower bounded by

$$h(f_\sigma, K) \geq \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} \check{\chi}_p \rho_p(t), 0 \right\}. \quad (19)$$

Note that: (1) The upper bound (17) holds regardless of the induced norm with which the matrix measures in (16) are computed, as long as the same one is used for all modes. (2) The bounds (17) and (19) are formulated in terms of asymptotic weighted averages of the constants  $\hat{\mu}_p$  and  $\check{\chi}_p$  defined by (16) and (18), respectively, with the active rates  $\rho_p(t)$  as weights. (3) Due to the upper limit in (16), the upper bound (17) depends on the values of Jacobian matrices  $J_x f_p(x)$  over only the  $\omega$ -limit set from the convex hull of initial set,  $\text{co}(K)$ , instead of all reachable points from  $\text{co}(K)$ . In particular, (17) is able to yield a finite bound in the case of unbounded Jacobian matrices but a compact  $\omega$ -limit set. This property is obtained using a result on asymptotic weighted averages established in Lemma 7 in Sect. 6.3, and similar properties hold for all bounds for entropy in this paper. (4) Provided that the constants  $\hat{\mu}_p$  and  $\check{\chi}_p$  are finite for all persistent modes  $p \in \mathcal{P}_\infty$ , the bounds (17) and (19) depend on their values over only the strongly persistent modes  $p \in \mathcal{P}_\infty^+$  (as the rest disappears after taking the asymptotic weighted average; see the proof of Lemma 7 for more details). However, if there exists a mode  $p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+$  such that  $\hat{\mu}_p$  or  $\check{\chi}_p$  is infinite, then the corresponding bound may not hold.

**Remark 3** The bounds (17) and (19) can be extended to some cases where the constants  $\mu_p$  and  $\check{\chi}_p$  are infinite. For example, (19) still holds if  $\check{\chi}_p \in \mathbb{R} \cup \{+\infty\}$  for all  $p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+$  and  $\check{\chi}_p \in \mathbb{R}$  for all  $p \in \mathcal{P}_\infty^+$ . Moreover, if  $\check{\chi}_p \in \mathbb{R} \cup \{+\infty\}$  for all  $p \in \mathcal{P}_\infty$ , and there exists a mode  $q \in \mathcal{P}_\infty^+$  such that  $\check{\chi}_q = +\infty$ , then the entropy of (2) satisfies  $h(f_\sigma, K) = +\infty$ . The proofs are along the lines of that of Theorem 1 and thus omitted here (see also Remark 9 in Sect. 6.3). Similar extensions can be made for the upper bound (17) as well as all bounds for entropy of switched systems in this paper.

**Remark 4** In many scenarios, we can construct simpler but more conservative bounds for entropy based on those in Theorem 1. For example, let  $S \subset \mathbb{R}^n$  be a set such that one of the following holds:



1.  $S = \mathbb{R}^n$ ;
2.  $S$  is compact and positively invariant for (2) and contains the convex hull of initial set,  $\text{co}(K)$ ; or
3.  $S$  is compact and contains the  $\omega$ -limit set from  $\text{co}(K)$ .

Suppose that there exists a family of constants  $\hat{\mu}_p^*$  for  $p \in \mathcal{P}_\infty^+$  such that  $\hat{\mu}_p^* \geq \mu(J_x f_p(v))$  for all  $p \in \mathcal{P}_\infty^+$  and  $v \in S$ . Then the upper bound (17) holds with  $\hat{\mu}_p^*$  in place of  $\hat{\mu}_p$ . Similar variants hold for all bounds for entropy in this paper. In the numerical examples in Sect. 5, the computation will be simplified based on the third scenario here.

Thinking of the nonswitched case as a switched system with constant switched signal, Theorem 1 implies the following upper and lower bounds for the entropy of a time-invariant system.

**Corollary 1** *The topological entropy of a time-invariant system  $\dot{x} = f(x)$  with state  $x \in \mathbb{R}^n$  satisfies*

$$\max\{\check{\chi}, 0\} \leq h(f, K) \leq \max\{n\hat{\mu}, 0\} \quad (20)$$

with

$$\check{\chi} := \liminf_{t \rightarrow \infty} \min_{v \in \xi(t, K)} \text{tr}(J_x f(v)), \quad \hat{\mu} := \limsup_{t \rightarrow \infty} \max_{v \in \xi(t, \text{co}(K))} \mu(J_x f(v)).$$

Based on the upper bound (17), we construct additional upper bounds for the entropy of (2) that require less information about the switching signal.

**Corollary 2** *Given a switching signal  $\sigma$ , consider the asymptotic active rates  $\hat{\rho}_p$  defined by (10) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). If the constants  $\hat{\mu}_p$  defined by (16) are finite for all  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched system (2) is upper bounded by*

$$h(f_\sigma, K) \leq \sum_{p \in \mathcal{P}_\infty^+} \max\{n\hat{\mu}_p, 0\} \hat{\rho}_p \quad (21)$$

and also by

$$h(f_\sigma, K) \leq \max_{p \in \mathcal{P}_\infty^+} \max\{n\hat{\mu}_p, 0\}. \quad (22)$$

Note that the upper bound (21) can be seen as an average of the results of applying the second inequality in (20) to each strongly persistent mode of (2) while omitting its inactive time, weighted by the corresponding asymptotic active rate  $\hat{\rho}_p$ ; the upper bound (22) can be seen as a maximum of these results over strongly persistent modes. Similar properties hold for the corresponding bounds in the cases with interconnected and block-diagonal structures in Sects. 4.1 and 5.2, respectively.

**Proof of Corollary 2** First, as the upper limit is a subadditive function, the upper bound (17) implies that

$$\begin{aligned} h(f_\sigma, K) &\leq \max \left\{ \sum_{p \in \mathcal{P}_\infty^+} \limsup_{t \rightarrow \infty} n \hat{\mu}_p \rho_p(t), 0 \right\} \\ &\leq \sum_{p \in \mathcal{P}_\infty^+} \max\{n \hat{\mu}_p, 0\} \limsup_{t \rightarrow \infty} \rho_p(t) = \sum_{p \in \mathcal{P}_\infty^+} \max\{n \hat{\mu}_p, 0\} \hat{\rho}_p. \end{aligned}$$

Second, (17) also implies that

$$\begin{aligned} h(f_\sigma, K) &\leq \max \left\{ \limsup_{t \rightarrow \infty} \left( \max_{p \in \mathcal{P}_\infty^+} n \hat{\mu}_p \right) \sum_{p \in \mathcal{P}_\infty^+} \rho_p(t), 0 \right\} \\ &\leq \max \left\{ \max_{p \in \mathcal{P}_\infty^+} n \hat{\mu}_p, 0 \right\} = \max_{p \in \mathcal{P}_\infty^+} \max\{n \hat{\mu}_p, 0\}. \end{aligned}$$

□

The results in Theorem 1 and Corollary 2 are compared in Remark 5; for a numerical example, see Example 1 in Sect. 5.1.

- Remark 5** 1. The upper bound (17) is less conservative than or equivalent to the upper bounds (21) and (22), while (21) and (22) are both useful in the sense that neither is less conservative, as it is possible that  $\sum_{p \in \mathcal{P}} \hat{\rho}_p > 1$  for the asymptotic active rates  $\hat{\rho}_p$ .
2. For a fixed family of modes, the upper bounds (21) and (22) require less information about the switching signal than the upper bound (17), as the former two depend on the asymptotic active rates  $\hat{\rho}_p$  instead of the active rates  $\rho_p(t)$ . Moreover, if for each  $p \in \mathcal{P}_\infty^+$ , a constant  $\hat{\mu}_p^*$  as in the first two scenarios in Remark 4 is used in place of  $\hat{\mu}_p$ , then (22) yields the same upper bound for all switching signals such that all modes are strongly persistent (i.e.,  $\mathcal{P}_\infty^+ = \mathcal{P}_\infty = \mathcal{P}$ ).

Consider the case where the modes of the switched system (2) are all linear, that is, there is a family of matrices  $A_p \in \mathbb{R}^{n \times n}$  for  $p \in \mathcal{P}$  such that

$$f_p(x) = A_p x \quad \forall p \in \mathcal{P}, x \in \mathbb{R}^n.$$

Then the constants  $\hat{\mu}_p$  and  $\check{\chi}_p$  defined by (16) and (18) satisfy

$$\hat{\mu}_p = \mu(A_p), \quad \check{\chi}_p = \text{tr}(A_p) \quad \forall p \in \mathcal{P}.$$

Therefore, Theorem 1 and Corollary 2 extend [50, Th. 1 and Remark 5] for the case of linear modes to the case of nonlinear modes, respectively, and improve them by considering persistent and strongly persistent modes.

## 4 Entropy of switched interconnected systems

### 4.1 General switched interconnected systems

Consider the case where the switched system (2) is a network of  $m \geq 2$  interconnected subsystems. For  $i \in \{1, \dots, m\}$ , we denote by  $x_i \in \mathbb{R}^{n_i}$  the state of the  $i$ th subsystem, and by  $f_p^i$  the corresponding components of the function  $f_p$  in mode  $p$  of (2) for  $p \in \mathcal{P}$ . Then (2) can be written as the *switched interconnected system*

$$\dot{x}_i = f_{\sigma}^i(x_1, \dots, x_m), \quad i \in \{1, \dots, m\} \quad (23)$$

with state  $x = (x_1, \dots, x_m) \in \mathbb{R}^n$  and functions  $f_p(x) = (f_p^1(x), \dots, f_p^m(x))$  for  $p \in \mathcal{P}$ . For brevity, we denote by  $J_{x_j} f_p^i(v) := J_{x_j} f_p^i(x)|_{x=v}$  the Jacobian matrix of function  $f_p^i(x)$  in mode  $p$  of the  $i$ th subsystem of (23) with respect to state  $x_j$  of the  $j$ th subsystem at  $x = v$ .

In this subsection, we show that the upper bound (17) for the topological entropy of the general switched nonlinear system (2) can be readily applied to derive upper bounds for the entropy of (23) that depend only on “network-level” information. Following [36], we assume that the following norms are given:

1. a “local” norm  $|\cdot|_i$  on  $\mathbb{R}^{n_i}$  for each  $i \in \{1, \dots, m\}$ , and
2. a monotone “network” norm  $|\cdot|_N$  on  $\mathbb{R}^m$ , that is, for all  $v, w \in \mathbb{R}^m$ , we have<sup>1</sup>

$$v \geq w \geq 0 \implies |v|_N \geq |w|_N.$$

In particular, all  $p$ -norms with  $p \geq 1$  are monotone.

For a vector  $v = (v_1, \dots, v_m) \in \mathbb{R}^n$  with  $v_i \in \mathbb{R}^{n_i}$  for  $i \in \{1, \dots, m\}$ , we define a “global” norm  $|\cdot|_G$  by

$$|v|_G := (|v_1|_1, \dots, |v_m|_m)|_N. \quad (24)$$

Clearly, as  $|\cdot|_N$  is monotone,  $|\cdot|_G$  is indeed a norm. We denote by  $\|\cdot\|_i$ ,  $\|\cdot\|_N$ , and  $\|\cdot\|_G$  the corresponding induced norms on  $\mathbb{R}^{n_i \times n_i}$ ,  $\mathbb{R}^{m \times m}$ , and  $\mathbb{R}^{n \times n}$ , respectively, and by  $\mu_i$ ,  $\mu_N$ , and  $\mu_G$  the corresponding matrix measures. We also denote by  $\|\cdot\|_{ij}$  the induced norm on  $\mathbb{R}^{n_i \times n_j}$  defined by

$$\|A\|_{ij} := \max_{|v|=1} |Av|_i, \quad i, j \in \{1, \dots, m\} : i \neq j.$$

As the “network” norm  $|\cdot|_N$  is monotone, the induced norm  $\|\cdot\|_N$  and matrix measure  $\mu_N$  satisfy similar monotonicity properties for nonnegative and Metzler matrices, respectively:

<sup>1</sup> In this subsection, an inequality between two vectors or matrices of the same size, or between a vector or matrix and a scalar, is to be interpreted entrywise (e.g.,  $A \geq 0$  means that  $A$  is a nonnegative matrix).

**Lemma 2** 1. For all nonnegative matrices  $A, B \in \mathbb{R}_{\geq 0}^{m \times m}$ , we have

$$A \geq B \implies \|A\|_N \geq \|B\|_N. \quad (25)$$

2. For all Metzler matrices  $A, B \in \mathbb{R}^{m \times m}$ , that is, matrices with nonnegative off-diagonal entries, we have

$$A \geq B \implies \mu_N(A) \geq \mu_N(B). \quad (26)$$

**Proof** 1. The implication in (25) follows from the definition of induced norm and monotonicity of  $|\cdot|_N$ . More specifically, let  $\bar{v} \in \arg \max_{|v|_N=1} |Bv|_N$ . Then  $\bar{v} \geq 0$  as  $B \geq 0$  and  $|\cdot|_N$  is monotone. Hence,  $\|A\|_N \geq |A\bar{v}|_N \geq |B\bar{v}|_N = \|B\|_N$  as  $A \geq B \geq 0$  and  $|\cdot|_N$  is monotone.

2. The implication in (26) follows from (25) and the definition of matrix measure (12). More specifically, we have

$$\mu_N(A) = \lim_{t \searrow 0} \frac{\|I + tA\|_N - 1}{t} \geq \lim_{t \searrow 0} \frac{\|I + tB\|_N - 1}{t} = \mu_N(B),$$

where the inequality follows from (25) as  $I + tA \geq I + tB \geq 0$  for the Metzler matrices  $A \geq B$  and small enough  $t > 0$ .

□

**Theorem 2** Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). Let

$$\hat{\mu}_p^N := \limsup_{t \rightarrow \infty: \sigma(t)=p} \max_{v \in \xi_\sigma(t, \text{co}(K))} \mu_N(A_p^N(v)), \quad p \in \mathcal{P} \quad (27)$$

with the matrix-valued functions  $A_p^N(v) = [a_p^{ij}(v)] \in \mathbb{R}^{m \times m}$  defined by

$$a_p^{ii}(v) := \mu_i(J_{x_i} f_p^i(v)), \quad a_p^{ij}(v) := \|J_{x_j} f_p^i(v)\|_{ij}, \quad i, j \in \{1, \dots, m\} : i \neq j. \quad (28)$$

If the constants  $\hat{\mu}_p^N$  are finite for all  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched interconnected system (23) is upper bounded by

$$h(f_\sigma, K) \leq \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} n \hat{\mu}_p^N \rho_p(t), 0 \right\}. \quad (29)$$

**Proof** The upper bound (29) follows from the general upper bound (17) as the constants  $\hat{\mu}_p$  defined by (16) with matrix measure  $\mu_G$  satisfy  $\hat{\mu}_p \leq \hat{\mu}_p^N$  for all  $p \in \mathcal{P}_\infty$ , which can be established using Lemma 3. □

**Lemma 3** ([36, Th. 2]) Consider a block matrix  $A = [A_{ij}] \in \mathbb{R}^{n \times n}$  with  $A_{ij} \in \mathbb{R}^{n_i \times n_j}$  for  $i, j \in \{1, \dots, m\}$ . Let  $A_N = [a_{ij}] \in \mathbb{R}^{m \times m}$  be a Metzler matrix such that

$$a_{ii} \geq \mu_i(A_{ii}), \quad a_{ij} \geq \|A_{ij}\|_{ij} \quad \forall i, j \in \{1, \dots, m\} : i \neq j.$$

Then

$$\mu_G(A) \leq \mu_N(A_N).$$

The next result shows that the upper limit and maximum in (27) can also be taken entrywise.

**Corollary 3** Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). Let

$$\hat{a}_p^{ij} := \limsup_{t \rightarrow \infty: \sigma(t)=p} \max_{v \in \xi_\sigma(t, \text{co}(K))} a_p^{ij}(v), \quad i, j \in \{1, \dots, m\}, \quad p \in \mathcal{P} \quad (30)$$

with the functions  $a_p^{ij}(v)$  defined by (28). If the constants  $\hat{a}_p^{ij}$  are finite for all  $i, j \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched interconnected system (23) is upper bounded by

$$h(f_\sigma, K) \leq \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} n \mu_N(\hat{A}_p^N) \rho_p(t), 0 \right\} \quad (31)$$

with the matrices  $\hat{A}_p^N = [\hat{a}_p^{ij}] \in \mathbb{R}^{m \times m}$ .

**Proof** Note that the matrices  $A_p^N(v) = [a_p^{ij}(v)]$  and  $\hat{A}_p^N = [\hat{a}_p^{ij}]$  defined by (28) and (30) are all Metzler matrices. Moreover, the upper limit in (30) imply that, for an arbitrary  $\delta > 0$ , there is a large enough  $t_\delta \geq 0$  such that

$$\max_{v \in \xi_\sigma(t, \text{co}(K))} a_p^{ij}(v) \leq \hat{a}_p^{ij} + \delta \quad \forall i, j \in \{1, \dots, m\}, \quad p \in \mathcal{P}_\infty, \quad t > t_\delta : \sigma(t) = p.$$

Then (26) implies that

$$\max_{v \in \xi_\sigma(t, \text{co}(K))} \mu_N(A_p^N(v)) \leq \mu_N(\hat{A}_p^N + \delta \mathbf{1}_{m \times m}) \leq \mu_N(\hat{A}_p^N) + \delta \mu_N(\mathbf{1}_{m \times m})$$

for all  $p \in \mathcal{P}_\infty$  and  $t > t_\delta$  such that  $\sigma(t) = p$ , where the last inequality follows from (14). Hence, the constants  $\hat{\mu}_p^N$  defined by (27) satisfy  $\hat{\mu}_p^N \leq \mu_N(\hat{A}_p^N)$  for all  $p \in \mathcal{P}_\infty$  as  $\delta > 0$  is arbitrary. Then (31) follows from the upper bound (29).  $\square$

Thinking of the nonswitched case as a switched system with constant switched signal, Theorem 2 and Corollary 3 imply the following upper bounds for the entropy of a time-invariant interconnected system.

**Corollary 4** *The topological entropy of a time-invariant interconnected system*

$$\dot{x}_i = f^i(x_1, \dots, x_m), \quad i \in \{1, \dots, m\} \quad (32)$$

with states  $x_i \in \mathbb{R}^{n_i}$  and  $x = (x_1, \dots, x_m) \in \mathbb{R}^n$  and functions  $f(x) = (f^1(x), \dots, f^m(x))$  is upper bounded by

$$h(f, K) \leq \max \left\{ \limsup_{t \rightarrow \infty} \max_{v \in \xi(t, \text{co}(K))} n\mu_N(A^N(v)), 0 \right\} \leq \max\{n\mu_N(\hat{A}^N), 0\} \quad (33)$$

with the matrix-valued function  $A^N(v) = [a^{ij}(v)] \in \mathbb{R}^{m \times m}$  defined by

$$a^{ii}(v) := \mu_i(J_{x_i} f^i(v)), \quad a^{ij}(v) := \|J_{x_j} f^i(v)\|_{i,j}, \quad i, j \in \{1, \dots, m\} : i \neq j, \quad (34)$$

and the matrix  $\hat{A}^N = [\hat{a}^{ij}] \in \mathbb{R}^{m \times m}$  defined by

$$\hat{a}^{ij} := \limsup_{t \rightarrow \infty} \max_{v \in \xi(t, \text{co}(K))} a^{ij}(v), \quad i, j \in \{1, \dots, m\}. \quad (35)$$

A similar upper bound for the entropy of (32) was constructed in [26, Th. 1]:

$$h(f, K) \leq \max\{n\lambda_{\max}(\tilde{A}^N), 0\}, \quad (36)$$

where  $\lambda_{\max}(\tilde{A}^N)$  is the largest real part of the eigenvalues of a matrix  $\tilde{A}^N \in \mathbb{R}^{m \times m}$  satisfying

$$\tilde{A}^N \geq A^N(v) \quad \forall v \in \mathbb{R}^n$$

with the matrix-valued function  $A^N(v) = [a^{ij}(v)]$  defined by (34).<sup>2</sup> The upper bounds given by the inequalities in (33) and (36) are both useful in the sense that neither is less conservative. On one hand, (36) may be less conservative due to the second inequality in (13). On the other hand, (36) may be more conservative as the matrix  $\hat{A}^N = [\hat{a}^{ij}]$  defined by (35) depends on the values of  $a^{ij}(v)$  over only the  $\omega$ -limit set from  $\text{co}(K)$ , instead of the entire  $\mathbb{R}^n$ .

Based on the upper bounds (29) and (31), we construct additional upper bounds for the entropy of (23) that require less information about the switching signal; the proof is along the lines of that of Corollary 2 and thus omitted here. The relations between them are similar to those between (17), (21), and (22) described in Remark 5.

**Corollary 5** *Given a switching signal  $\sigma$ , consider the asymptotic active rates  $\hat{\rho}_p$  defined by (10) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). If the constants  $\hat{\mu}_p^N$  and  $\hat{a}_p^{ij}$  defined by (27) and (30) are finite for all  $i, j \in$*

<sup>2</sup> Note that  $\tilde{A}^N$  has to be a Metzler matrix; thus, its eigenvalue with the largest real part is real [10, Th. 10.2, p. 167].

$\{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched interconnected system (23) is upper bounded by

$$h(f_\sigma, K) \leq \sum_{p \in \mathcal{P}_\infty^+} \max\{n\hat{\mu}_p^N, 0\} \hat{\rho}_p \leq \sum_{p \in \mathcal{P}_\infty^+} \max\{n\mu_N(\hat{A}_p^N), 0\} \hat{\rho}_p$$

and also by

$$h(f_\sigma, K) \leq \max_{p \in \mathcal{P}_\infty^+} \max\{n\hat{\mu}_p^N, 0\} \leq \max_{p \in \mathcal{P}_\infty^+} \max\{n\mu_N(\hat{A}_p^N), 0\}$$

with the matrices  $\hat{A}_p^N = [\hat{a}_p^{ij}] \in \mathbb{R}^{m \times m}$ .

## 4.2 Switched block-diagonal systems

Consider the case where the dynamics of the  $m \geq 2$  subsystems of the switched interconnected system (23) are independent. Specifically, for each  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}$ , the function  $f_p^i(x_1, \dots, x_m)$  is independent of  $x_j$  for all  $j \neq i$ . For brevity, we regard it as a function on  $\mathbb{R}^{n_i}$  and rewrite it as  $f_p^i(x_i)$ . Then (23) can be written as a *switched block-diagonal system*

$$\dot{x}_i = f_\sigma^i(x_i), \quad i \in \{1, \dots, m\} \quad (37)$$

with functions  $f_p(x) = (f_p^1(x_1), \dots, f_p^m(x_m))$  for  $p \in \mathcal{P}$ . Clearly, the solution to the  $i$ th subsystem of (37) is independent of the initial states of other subsystems. For brevity, we denote it by  $\xi_\sigma^i(t, x_i)$  and the corresponding reachable set by  $\hat{\xi}_\sigma^i(t, K_i)$ , where  $K_i \subset \mathbb{R}^{n_i}$  is the corresponding projection of the initial set  $K$ .

In this subsection, we construct upper and lower bounds for the topological entropy of (37) that are less conservative than the results of simply applying the general bounds from Sect. 4.1 to (37). Let the “local,” “network,” and “global” norms  $|\cdot|_i$  for  $i \in \{1, \dots, m\}$ ,  $|\cdot|_N$ , and  $|\cdot|_G$ , and the corresponding induced norms  $\|\cdot\|_i$ ,  $\|\cdot\|_N$ , and  $\|\cdot\|_G$  and matrix measures  $\mu_i$ ,  $\mu_N$ , and  $\mu_G$  be given as in Sect. 4.1.

The following result provides upper and lower bound for the entropy of (37); the proof can be found in Sect. 6.4.

**Theorem 3** *Given a switching signal  $\sigma$ , consider the active times  $\tau_p(t)$  defined by (8) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11).*

1. *Let*

$$\hat{\mu}_p^i := \limsup_{t \rightarrow \infty: \sigma(t)=p} \max_{v_i \in \xi_\sigma^i(t, \text{co}(K_i))} \mu_i(J_{x_i} f_p^i(v_i)), \quad i \in \{1, \dots, m\}, p \in \mathcal{P}. \quad (38)$$

If the constants  $\hat{\mu}_p^i$  are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is upper bounded by

$$h(f_\sigma, K) \leq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} n_i \hat{\mu}_p^i \tau_p(t). \quad (39)$$

2. Let

$$\check{\mu}_p^i := \liminf_{t \rightarrow \infty: \sigma(t)=p} \min_{v_i \in \text{co}(\xi_\sigma^i(t, K_i))} -\mu_i(-J_{x_i} f_p^i(v_i)), \quad i \in \{1, \dots, m\}, p \in \mathcal{P}. \quad (40)$$

If the constants  $\check{\mu}_p^i$  are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is lower bounded by

$$h(f_\sigma, K) \geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} n_i \check{\mu}_p^i \tau_p(t). \quad (41)$$

The following result provides an alternative lower bound for the entropy of (37); the proof can be found in Sect. 6.5.

**Theorem 4** Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). Let

$$\check{\chi}_p^i := \liminf_{t \rightarrow \infty: \sigma(t)=p} \min_{v_i \in \xi_\sigma^i(t, K_i)} \text{tr}(J_{x_i} f_p^i(v_i)), \quad i \in \{1, \dots, m\}, p \in \mathcal{P}. \quad (42)$$

If the constants  $\check{\chi}_p^i$  are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is lower bounded by

$$h(f_\sigma, K) \geq \limsup_{t \rightarrow \infty} \sum_{i=1}^m \max \left\{ \sum_{p \in \mathcal{P}_\infty^+} \check{\chi}_p^i \rho_p(t), 0 \right\}. \quad (43)$$

Thinking of the nonswitched case as a switched system with constant switched signal, Theorems 3 and 4 imply the following upper and lower bounds for the entropy of a time-invariant block-diagonal system.

**Corollary 6** The topological entropy of a time-invariant block-diagonal system  $\dot{x}_i = f^i(x_i)$  for  $i \in \{1, \dots, m\}$  with states  $x_i \in \mathbb{R}^{n_i}$  and  $x = (x_1, \dots, x_m) \in \mathbb{R}^n$  and functions  $f(x) = (f^1(x_1), \dots, f^m(x_m))$  satisfies

$$\sum_{i=1}^m \max\{\check{\chi}^i, 0\} \leq h(f, K) \leq \sum_{i=1}^m \max\{n_i \hat{\mu}^i, 0\}$$



with

$$\begin{aligned}\check{\chi}^i &:= \liminf_{t \rightarrow \infty} \min_{v_i \in \xi^i(t, K_i)} \operatorname{tr}(J_{x_i} f^i(v_i)), \\ \hat{\mu}^i &:= \limsup_{t \rightarrow \infty} \max_{v_i \in \xi^i(t, \operatorname{co}(K_i))} \mu_i(J_{x_i} f^i(v_i)),\end{aligned}\quad i \in \{1, \dots, m\},$$

where  $K_i \subset \mathbb{R}^{n_i}$  is the corresponding projection of the initial set  $K$ .

Based on the upper bound (39), we construct additional upper bounds for the entropy of (37) by considering each subsystem or each mode separately.

**Corollary 7** *Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). If the constants  $\hat{\mu}_p^i$  defined by (38) are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is upper bounded by*

$$h(f_\sigma, K) \leq \sum_{i=1}^m \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} n_i \hat{\mu}_p^i \rho_p(t), 0 \right\}. \quad (44)$$

**Proof** As the upper limit is a subadditive function, the upper bound (39) implies that

$$h(f_\sigma, K) \leq \sum_{i=1}^m \limsup_{T \rightarrow \infty} \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} n_i \hat{\mu}_p^i \tau_p(t).$$

Then we obtain (44) by invoking the second equality in (71) for each  $i \in \{1, \dots, m\}$  with the constants  $c_p = n_i \hat{\mu}_p^i$  for  $p \in \mathcal{P}_\infty^+$ .  $\square$


**Corollary 8** *Given a switching signal  $\sigma$ , consider the active rates  $\rho_p(t)$  defined by (9) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). If the constants  $\hat{\mu}_p^i$  defined by (38) are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is upper bounded by*

$$h(f_\sigma, K) \leq \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} \left( \sum_{i=1}^m \max\{n_i \hat{\mu}_p^i, 0\} \right) \rho_p(t). \quad (45)$$

**Proof** As the active times  $\tau_p(t)$  are nondecreasing, the upper bound (39) implies that

$$h(f_\sigma, K) \leq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \sum_{p \in \mathcal{P}_\infty^+} \max\{n_i \hat{\mu}_p^i, 0\} \rho_p(T).$$

Then we obtain (45) by grouping together the terms for the same mode.  $\square$



**Fig. 1** Relations between the upper bounds (39), (44), (45), (46), and (47). The implications (A) and (B) become equivalence if the active rates  $\rho_p(t)$  converge for all  $p \in \mathcal{P}_\infty^+$ ; the implication (C) becomes equivalence if the constants  $\hat{\mu}_p^i \geq 0$  for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty^+$ ; the implication (D) becomes equivalence if both of these conditions hold

Based on the upper bounds (44) and (45), we also construct additional upper bounds for the entropy of (37) that require less information about the switching signal; the proof is along the lines of that of Corollary 2 and thus omitted here.

**Corollary 9** *Given a switching signal  $\sigma$ , consider the asymptotic active rates  $\hat{\rho}_p$  defined by (10) and the sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). If the constants  $\hat{\mu}_p^i$  defined by (38) are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then the topological entropy of the switched block-diagonal system (37) is upper bounded by*

$$h(f_\sigma, K) \leq \sum_{p \in \mathcal{P}_\infty^+} \left( \sum_{i=1}^m \max\{n_i \hat{\mu}_p^i, 0\} \right) \hat{\rho}_p \quad (46)$$

and also by

$$h(f_\sigma, K) \leq \max_{p \in \mathcal{P}_\infty^+} \sum_{i=1}^m \max\{n_i \hat{\mu}_p^i, 0\}. \quad (47)$$

The results in Theorems 1, 3, and 4 and Corollaries 7, 8, and 9 are compared in Fig. 1 and Remark 6; for a numerical example, see Example 2 in Sect. 5.2.

- Remark 6**
1. The upper bound (39) is less conservative than or equivalent to the upper bounds (44) and (45), while (44) is less conservative than or equivalent to the upper bound (46), and (45) is less conservative than or equivalent to the upper bounds (46) and (47). The upper bounds (44) and (45) are both useful in the sense that neither is less conservative (cf. Fig. 1). The same holds for the upper bounds (46) and (47) (cf. item 1 of Remark 5), and also for the lower bounds (41) and (43).
  2. As explained in the proof of Theorem 1 in Sect. 6.6, the upper bound (17) and lower bound (19) for the entropy of the general switched nonlinear systems can be obtained by taking  $m = 1$  and  $n_1 = n$  in the bounds (44) and (43), respectively. For the switched block-diagonal system (37), the bounds (44), (43), (46), and (47) are less conservative than or equivalent to the bounds (17), (19), (21), and (22), respectively.
  3. For a fixed family of modes, the upper bounds (46) and (47) require less information about the switching signal than the upper bounds (39), (44), and (45), as the former

two depend on the asymptotic active rates  $\hat{\rho}_p$  instead of the active times  $\tau_p(t)$  and active rates  $\rho_p(t)$ . Moreover, if for each  $p \in \mathcal{P}_\infty^+$ , a constant  $\hat{\mu}_p^*$  as in the first two scenarios in Remark 4 is used in place of  $\hat{\mu}_p$ , then (47) yields the same upper bound for all switching signals such that all modes are strongly persistent (i.e.,  $\mathcal{P}_\infty^+ = \mathcal{P}_\infty = \mathcal{P}$ ).

Consider the case where the subsystems of the switched block-diagonal system (37) are all scalar and their modes are all linear, that is, there is a family of diagonal matrices  $D_p = \text{diag}(a_p^1, \dots, a_p^n) \in \mathbb{R}^{n \times n}$  for  $p \in \mathcal{P}$  such that

$$f_p^i(x_i) = a_p^i x_i \quad \forall i \in \{1, \dots, n\}, p \in \mathcal{P}, (x_1, \dots, x_n) \in \mathbb{R}^n. \quad (48)$$

Then the constants  $\hat{\mu}_p^i$ ,  $\check{\mu}_p^i$ , and  $\check{\chi}_p^i$  defined by (38), (40), and (42) satisfy

$$\hat{\mu}_p^i = \check{\mu}_p^i = \check{\chi}_p^i = a_p^i, \quad \forall i \in \{1, \dots, n\}, p \in \mathcal{P}.$$

Therefore, Theorem 3 and Corollaries 7, 8, and 9 extend [48, Th. 7, Prop. 8 and 9, and Cor. 10] for the case of linear modes with diagonal structure to the case of nonlinear modes with block-diagonal structure, respectively, and improve them by considering persistent and strongly persistent modes. Moreover, the lower bound (43) is novel even in the former case, which is presented in the following corollary.

**Corollary 10** *The topological entropy of the switched linear diagonal system (48) is lower bounded by*

$$h(D_\sigma) \geq \limsup_{t \rightarrow \infty} \sum_{i=1}^n \max \left\{ \sum_{p \in \mathcal{P}_\infty^+} a_p^i \rho_p(t), 0 \right\}. \quad (49)$$

Theorem 3 and Corollaries 7 and 9 also extend [51, Th. 4.1 and Cor 4.2] for the case of diagonal structure to the case of block-diagonal structure. Moreover, due to the upper limit in (38), the upper bound (39) depends on the values of Jacobian matrices  $J_{x_i} f_p^i(x_i)$  over only the  $\omega$ -limit set from the convex hull of initial set,  $\text{co}(K)$ , whereas the upper bound [51, eq. (39)] involves all reachable points from  $\text{co}(K)$ .

## 5 Numerical examples

Consider the following switched nonlinear system in the nonnegative orthant  $\mathbb{R}_{\geq 0}^n$  from [2]:

$$\dot{x} = f_\sigma(x) := (r_\sigma + A_\sigma x) \circ x \quad (50)$$

with state  $x \in \mathbb{R}_{\geq 0}^n$ , switching signal  $\sigma : \mathbb{R}_{\geq 0} \rightarrow \mathcal{P}$ , and finite index set  $\mathcal{P}$ , where  $\circ$  denotes the Hadamard (entrywise) product. Equivalently, (50) can be written as

$$\dot{x}_i = \left( r_\sigma^i + \sum_{j=1}^n a_\sigma^{ij} x_j \right) x_i, \quad i \in \{1, \dots, n\}$$

with  $x = (x_1, \dots, x_n)$  and  $r_p = (r_p^1, \dots, r_p^n)$  and  $A_p = [a_p^{ij}]$  for  $p \in \mathcal{P}$ . Each mode  $p$  of (50) is a Lotka–Volterra ecosystem model that describes the population dynamics of  $n$  species in a biological community [17, Ch. 5], where  $x_i$  is the population density of the  $i$ th species,  $r_p^i \in \mathbb{R}$  quantifies its intrinsic growth rate,  $a_p^{ii} < 0$  is a self-interaction term justified by the limitation of resources in the environment, and  $a_p^{ij} \in \mathbb{R}$  for  $j \neq i$  is an interaction term quantifying the influence of the  $j$ th species on the  $i$ th one. Switching in (50) may be due to seasonal changes or environment fluctuations. Clearly,  $\mathbb{R}_{\geq 0}^n$  is a positively invariant set for the switched system (50).

We construct two switching signals  $\sigma_1, \sigma_2 : \mathbb{R}_{\geq 0} \rightarrow \mathcal{P} = \{1, 2\}$  as follows<sup>3</sup>:

- $\sigma_1$  with periodic switching: Let  $t_k := 1000k$  for  $k \geq 1$ . Simple computation shows that  $\hat{\rho}_1 = \hat{\rho}_2 = 0.5$ .
- $\sigma_2$  with constant setpoints: Let  $t_1 := 1$  and  $t_{2k} := \min\{t > t_{2k-1} : \rho_2(t) \geq 0.9\}$  and  $t_{2k+1} := \min\{t > t_{2k} : \rho_1(t) \geq 0.9\}$  for  $k \geq 1$ . Simple computation shows that  $t_k = 9^{k-1} + 9^{k-2}$  for  $k \geq 2$  and  $\hat{\rho}_1 = \hat{\rho}_2 = 0.9$ .

Clearly,  $\mathcal{P}_\infty^+ = \mathcal{P}_\infty = \mathcal{P}$  for both  $\sigma_1$  and  $\sigma_2$ .

## 5.1 A general case

Suppose that the matrices  $A_p = [a_p^{ij}]$  in the switched Lotka–Volterra system (50) satisfy

$$a_p^{ii} + \sum_{j \neq i} |a_p^{ij}| < 0, \quad a_p^{ii} + \sum_{j \neq i} |a_p^{ji}| < 0 \quad \forall i \in \{1, \dots, n\}, \quad p \in \mathcal{P}. \quad (51)$$


Then [2, Th. 3] implies that (50) is *uniformly ultimately bounded (UUB)* in  $\mathbb{R}_{\geq 0}^n$ , and its  $\omega$ -limit set is a subset of<sup>4</sup>

$$S := \prod_{i=1}^n \left[ 0, \max_{p \in \mathcal{P}} \max \left\{ -\frac{2r_p^i}{\lambda_{\max}(A_p + A_p^\top)}, 0 \right\} \right], \quad (52)$$

where  $\lambda_{\max}(A_p + A_p^\top)$  denotes the largest eigenvalue of the symmetric matrix  $A_p + A_p^\top$  and satisfies  $\lambda_{\max}(A_p + A_p^\top) < 0$  due to the condition (51), the formula for matrix measure (15), and the second inequality in (13).

<sup>3</sup> We denote by  $0 < t_1 < t_2 < \dots$  the sequence of switches and let  $t_0 := 0$ , with  $\sigma(t) = 1$  on  $[t_{2k}, t_{2k+1})$  and  $\sigma(t) = 2$  on  $[t_{2k+1}, t_{2k+2})$ .

<sup>4</sup> Specifically, following the proof of [2, Th. 3]  $S$  contains the  $\omega$ -limit set of (50) if for all  $p \in \mathcal{P}$  and  $x \in \mathbb{R}_{\geq 0}^n \setminus (S \cup \{0\})$ , we have  $\mathbf{1}_n^\top f_p(x) < 0$ , i.e.,  $r_p^\top x + x^\top A_p x < 0$ . Note that  $r_p^\top x + x^\top A_p x = r_p^\top x + x^\top (A_p + A_p^\top) x / 2 \leq (r_p + \lambda_{\max}(A_p + A_p^\top) x / 2)^\top x$ , which is negative if  $2r_p^i + \lambda_{\max}(A_p + A_p^\top) x_i < 0$  for all  $i \in \{1, \dots, n\}$  as  $x \in \mathbb{R}_{\geq 0}^n \setminus \{0\}$ .



**Fig. 2** Trajectories of the switched system in Example 1, for (a) individual mode 1 with initial states  $(4, 3)$ ,  $(4, 0.1)$ ,  $(4, 0)$ , and  $(10/3, 20/9)$ ; (b) individual mode 2 with initial states  $(4, 3)$ ,  $(0.1, 3)$ ,  $(0, 3)$ , and  $(10/3, 20/9)$ ; (c) switching signal  $\sigma_1$  with initial states  $(4, 3)$ ,  $(4, 0)$ , and  $(0, 3)$ ; (d) switching signal  $\sigma_2$  with initial state  $(4, 3)$ . The circles mark the beginning of a segment after switching. The dashed rectangles represent  $S = [0, 10/3] \times [0, 20/9]$

**Example 1** Consider the switched system (50) in  $\mathbb{R}_{\geq 0}^2$  with index set  $\mathcal{P} = \{1, 2\}$  and coefficients

$$r_1 = \begin{bmatrix} -1 \\ 2 \end{bmatrix}, \quad r_2 = \begin{bmatrix} 3 \\ -1 \end{bmatrix}, \quad A_1 = A_2 = \begin{bmatrix} -1 & 0.1 \\ 0.1 & -1 \end{bmatrix}.$$

Simple computation shows that mode 1 has an attractor  $(0, 2)$  and a saddle point  $(0, 0)$  with stable manifold  $\mathbb{R}_{\geq 0} \times \{0\}$ , and mode 2 has an attractor  $(3, 0)$  and a saddle point  $(0, 0)$  with stable manifold  $\{0\} \times \mathbb{R}_{\geq 0}$ . Moreover, the condition (51) holds and the set defined by (52) is given by  $S = [0, 10/3] \times [0, 20/9]$ . Typical trajectories of (50) for the individual modes 1 and 2 and the switching signals  $\sigma_1$  and  $\sigma_2$  are plotted in Fig. 2. In particular,  $S$  is not a positively invariant set.

**Table 1** Upper bounds for entropy in Example 1

	$(\hat{\rho}_1, \hat{\rho}_2)$	(17)	(21)	(22)
$\sigma_1$	(0.5, 0.5)	5.56	5.56	6.45
$\sigma_2$	(0.9, 0.9)	6.27	10	6.45

The Jacobian matrices of individual modes are given by

$$J_x f_1(v) = \begin{bmatrix} -1 - 2v_1 + 0.1v_2 & 0.1v_1 \\ 0.1v_2 & 2 + 0.1v_1 - 2v_2 \end{bmatrix},$$

$$J_x f_2(v) = \begin{bmatrix} 3 - 2v_1 + 0.1v_2 & 0.1v_1 \\ 0.1v_2 & -1 + 0.1v_1 - 2v_2 \end{bmatrix}$$

with  $v = (v_1, v_2) \in \mathbb{R}_{\geq 0}^2$ . As the switched system is UUB and its  $\omega$ -limit set is a subset of  $S$ , for all initial sets  $K \subset \mathbb{R}_{\geq 0}^2$ , one can obtain upper bounds for the constants  $\hat{\mu}_p$  defined by (16) by replacing the upper limit over  $\{t \geq 0 : \sigma(s) = p\}$  and maximum over  $\xi_\sigma(t, \text{co}(K))$  with a maximum over  $S$ , that is,

$$\hat{\mu}_1 \leq \max_{v \in S} \mu(J_x f_1(v)) = \max_{v \in S} \max\{-1 - 1.9v_1 + 0.1v_2, 2 + 0.1v_1 - 1.9v_2\} = 7/3,$$

$$\hat{\mu}_2 \leq \max_{v \in S} \mu(J_x f_2(v)) = \max_{v \in S} \max\{3 - 1.9v_1 + 0.1v_2, -1 + 0.1v_1 - 1.9v_2\} = 29/9,$$

where the matrix measures are computed with the induced  $\infty$ -norm using the formula (15).

The upper bounds for the entropies  $h(f_{\sigma_1}, K)$  and  $h(f_{\sigma_2}, K)$  computed using (17), (21), and (22) for all initial sets  $K \subset \mathbb{R}_{\geq 0}^2$  are summarized in Table 1.<sup>5</sup> In particular, the upper bound (17) for  $h(f_{\sigma_2}, K)$  can be computed as follows:

$$\begin{aligned} h(f_{\sigma_2}, K) &\leq \limsup_{t \rightarrow \infty} (2\hat{\mu}_1 \rho_1(t) + 2\hat{\mu}_2 \rho_2(t)) \\ &\leq \limsup_{t \rightarrow \infty} 2 \left( \frac{7}{3} (1 - \rho_2(t)) + \frac{29}{9} \rho_2(t) \right) = 2 \left( \frac{7}{3} + \left( \frac{29}{9} - \frac{7}{3} \right) \hat{\rho}_2 \right) \approx 6.27. \end{aligned}$$

The values in Table 1 are consistent with the relations between these upper bounds described in Remark 5.

## 5.2 A block-diagonal case

Consider the case where the switched Lotka–Volterra system (50) describes a biological community of  $m \geq 2$  groups of species, where the  $i$ th group consists of  $n_i$  species, and the dynamics of species from different groups are independent. Regarding

<sup>5</sup> In this example, we use the set  $S$  defined by (52) which contains the  $\omega$ -limit set for every switched system (50) satisfying (51). For a given family of coefficients, one can usually construct more precise over-approximation of the  $\omega$ -limit set and thus obtain less conservative upper bounds for entropy, such as those in [51, Example 3.6].

the groups as interconnected subsystems, we denote by  $\bar{x}_i \in \mathbb{R}_{\geq 0}^{n_i}$  the state of the  $i$ th subsystem, and by  $\bar{f}_p^i(\bar{x}_i)$ ,  $\bar{r}_p^i$ , and  $\bar{A}_p^i$  the corresponding function and coefficients of mode  $p$  to avoid confusion. Then (50) can be written as the switched block-diagonal system

$$\dot{\bar{x}}_i = \bar{f}_\sigma^i(\bar{x}_i) := (\bar{r}_\sigma^i + \bar{A}_\sigma^i \bar{x}_i) \circ \bar{x}_i, \quad i \in \{1, \dots, m\} \quad (53)$$

with state  $x = (\bar{x}_1, \dots, \bar{x}_k) \in \mathbb{R}^n$ , and functions  $f_p(x) = (\bar{f}_p^1(\bar{x}_1), \dots, \bar{f}_p^m(\bar{x}_m))$ , coefficients  $r_p = (\bar{r}_p^1, \dots, \bar{r}_p^m)$ , and matrices  $A_p = \text{diag}(\bar{A}_p^1, \dots, \bar{A}_p^m)$  for  $p \in \mathcal{P}$ .

For (53), the formula (15) implies that the condition (51) can be written as

$$\mu(\bar{A}_p^i), \mu((\bar{A}_p^i)^\top) < 0 \quad \forall i \in \{1, \dots, m\}, p \in \mathcal{P}, \quad (54)$$

where the matrix measures are computed with the induced  $\infty$ -norm. If (54) holds, then [2, Th. 3] implies that (53) is UUB in  $\mathbb{R}_{\geq 0}^n$ , and its  $\omega$ -limit set is a subset of

$$S := \prod_{j=1}^n \left[ 0, \max_{p \in \mathcal{P}} \max \left\{ -\frac{2r_p^j}{\lambda_{\max}(A_p^{i(j)} + (A_p^{i(j)})^\top)}, 0 \right\} \right], \quad (55)$$

where the  $j$ th species is in the  $i(j)$ th group, and  $\lambda_{\max}(A_p^{i(j)} + (A_p^{i(j)})^\top)$  denotes the largest eigenvalue of the symmetric matrix  $A_p^{i(j)} + (A_p^{i(j)})^\top$  and satisfies  $\lambda_{\max}(A_p^{i(j)} + (A_p^{i(j)})^\top) < 0$  due to the condition (54), the formula for matrix measure (15), and the second inequality in (13).


**Example 2** Consider the switched block-diagonal system (53) in  $\mathbb{R}_{\geq 0}^3$  with index set  $\mathcal{P} = \{1, 2\}$  and coefficients

$$\begin{aligned} \bar{r}_1^1 &= \begin{bmatrix} -1 \\ -1 \end{bmatrix}, & \bar{r}_2^1 &= \begin{bmatrix} 3 \\ 3 \end{bmatrix}, & \bar{A}_1^1 &= \bar{A}_2^1 = \begin{bmatrix} -1 & 0.1 \\ 0.1 & -1 \end{bmatrix}, \\ \bar{r}_1^2 &= 2, & \bar{r}_2^2 &= -1, & \bar{A}_1^2 &= \bar{A}_2^2 = -1. \end{aligned}$$

Simple computation shows that mode 1 has an attractor  $(0, 0, 2)$  and a saddle point  $(0, 0, 0)$  with stable manifold  $\mathbb{R}_{\geq 0}^2 \times \{0\}$ , and mode 2 has an attractor  $(10/3, 10/3, 0)$  and three saddle points  $(0, 0, 0)$ ,  $(3, 0, 0)$ , and  $(0, 3, 0)$  with stable manifolds  $\{(0, 0)\} \times \mathbb{R}_{\geq 0}$ ,  $\mathbb{R}_{>0} \times \{0\} \times \mathbb{R}_{\geq 0}$ , and  $\{0\} \times \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0}$ , respectively. Moreover, the condition (54) holds and the set defined by (55) is given by  $S = [0, 10/3]^2 \times [0, 2]$ . Typical trajectories of (53) for the individual modes 1 and 2 and the switching signals  $\sigma_1$  and  $\sigma_2$  are plotted in Fig. 3.

The Jacobian matrices of individual modes are given by

$$\begin{aligned} J_x f_1(v) &= \text{diag}(J_{\bar{x}_1} \bar{f}_1^1(\bar{v}_1), J_{\bar{x}_2} \bar{f}_1^2(\bar{v}_2)), \\ J_x f_2(v) &= \text{diag}(J_{\bar{x}_1} \bar{f}_2^1(\bar{v}_1), J_{\bar{x}_2} \bar{f}_2^2(\bar{v}_2)) \end{aligned}$$



**Fig. 3** Trajectories of the switched block-diagonal system in Example 2, for (a) individual mode 1 with initial states  $(4, 4, 3)$ ,  $(4, 4, 0.1)$ ,  $(4, 4, 0)$ , and  $(10/3, 10/3, 2)$ ; (b) individual mode 2 with initial states  $(4, 4, 3)$ ,  $(4, 0.1, 3)$ ,  $(0.1, 4, 3)$ ,  $(4, 0, 3)$ ,  $(0, 4, 3)$ ,  $(0.1, 0.1, 3)$ ,  $(0.1, 0, 3)$ ,  $(0, 0.1, 3)$ ,  $(0, 0, 3)$ , and  $(10/3, 10/3, 2)$ ; (c) switching signal  $\sigma_1$  with initial states  $(4, 4, 3)$ ,  $(4, 0, 3)$ ,  $(0, 4, 3)$ , and  $(0, 0, 3)$ ; (d) switching signal  $\sigma_2$  with initial states  $(4, 4, 3)$ ,  $(4, 0, 3)$ , and  $(0, 4, 3)$ . The circles mark the beginning of a segment after switching. The dashed hyperrectangles represent  $S = [0, 10/3]^2 \times [0, 2]$

with

$$\begin{aligned}
 J_{\bar{x}_1} \bar{f}_1^1(\bar{v}_1) &= \begin{bmatrix} -1 - 2v_1 + 0.1v_2 & 0.1v_1 \\ 0.1v_2 & -1 + 0.1v_1 - 2v_2 \end{bmatrix}, & J_{\bar{x}_2} \bar{f}_1^2(\bar{v}_2) &= 2 - 2v_3, \\
 J_{\bar{x}_1} \bar{f}_2^1(\bar{v}_1) &= \begin{bmatrix} 3 - 2v_1 + 0.1v_2 & 0.1v_1 \\ 0.1v_2 & 3 + 0.1v_1 - 2v_2 \end{bmatrix}, & J_{\bar{x}_2} \bar{f}_2^2(\bar{v}_2) &= -1 - 2v_3,
 \end{aligned}$$

where  $v = (\bar{v}_1, \bar{v}_2)$  with  $\bar{v}_1 = (v_1, v_2) \in \mathbb{R}_{\geq 0}^2$ , and  $\bar{v}_2 = v_3 \in \mathbb{R}_{\geq 0}$ . As the switched block-diagonal system is UUB and its  $\omega$ -limit set is a subset of  $S$ , for all initial sets



**Table 2** Upper bounds for entropy in Example 2

	$(\hat{\rho}_1, \hat{\rho}_2)$	(17)	(21)	(22)	(39)	(44)	(45)	(46)	(47)
$\sigma_1$	(0.5, 0.5)	8	8	10	3.17	3.17	4.34	4.34	6.67
$\sigma_2$	(0.9, 0.9)	9.6	14.4	10	6.06	7.57	6.2	7.8	6.67

$K \subset \mathbb{R}_{\geq 0}^3$ , one can obtain upper bounds for the constants  $\hat{\mu}_p$  and  $\hat{\mu}_p^i$  defined by (16) and (38) by replacing the upper limit over  $\{t \geq 0 : \sigma(s) = p\}$  and maximum over  $\xi_\sigma(t, \text{co}(K))$  and  $\xi_\sigma^i(t, \text{co}(K_i))$  with a maximum over  $S$ , that is,

$$\begin{aligned}\hat{\mu}_1^1 &\leq \max_{v \in S} \mu(J_{\bar{x}_1} \bar{f}_1^1(\bar{v}_1)) = \max_{v \in S} \max\{-1.9v_1 + 0.1v_2, 0.1v_1 - 1.9v_2\} - 1 = -2/3, \\ \hat{\mu}_1^2 &\leq \max_{v \in S} \mu(J_{\bar{x}_2} \bar{f}_1^2(\bar{v}_2)) = \max_{v \in S} 2 - 2v_3 = 2, \\ \hat{\mu}_2^1 &\leq \max_{v \in S} \mu(J_{\bar{x}_1} \bar{f}_2^1(\bar{v}_1)) = \max_{v \in S} \max\{3 - 1.9v_1 + 0.1v_2, 3 + 0.1v_1 - 1.9v_2\} = 10/3, \\ \hat{\mu}_2^2 &\leq \max_{v \in S} \mu(J_{\bar{x}_2} \bar{f}_2^2(\bar{v}_2)) = \max_{v \in S} -1 - 2v_3 = -1,\end{aligned}$$

and

$$\begin{aligned}\hat{\mu}_1 &\leq \max_{v \in S} \mu(J_x f_1(v)) = \max\{-2/3, 2\} = 2, \\ \hat{\mu}_2 &\leq \max_{v \in S} \mu(J_x f_2(v)) = \max\{10/3, -1\} = 10/3,\end{aligned}$$

where the matrix measures are computed with the induced  $\infty$ -norm using the formula (15).

The upper bounds for entropies  $h(f_{\sigma_1}, K)$  and  $h(f_{\sigma_2}, K)$  computed using (17), (21), (22), (39), (44), (45), (46), and (47) for all initial sets  $K \subset \mathbb{R}_{\geq 0}^3$  are summarized in Table 2. In particular, the upper bounds (17), (44), and (45) for  $h(f_{\sigma_2}, K)$  are computed along the lines of the computation of (17) in Example 1; the upper bound (39) is computed along the lines of the computation of  $h(D_{\sigma_2})$  in [50, Example 3]. The values in Table 2 are consistent with the relations between these upper bounds described in Fig. 1 and Remark 6.

## 6 Proofs of main results

In this section, we present the proofs of Theorems 1, 3, and 4, after introducing some necessary technical preliminaries.

### 6.1 Bounds for distance between solutions and volume of reachable set

We construct several upper and lower bounds for the distance between two solutions to the switched system (2) and a lower bound for the volume of its reachable set; the proofs can be found in “Appendix A.”

**Lemma 4** For all initial states  $x, \bar{x} \in K$ , the corresponding solutions to the switched system (2) satisfy

$$|\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| \leq e^{\bar{\eta}_\sigma(t)} |\bar{x} - x| \quad \forall t \geq 0 \quad (56)$$

with

$$\bar{\eta}_\sigma(t) := \max_{v \in \text{co}(K)} \sum_{p \in \mathcal{P}} \int_0^t \mu(J_x f_p(\xi_\sigma(s, v))) \mathbb{1}_p(\sigma(s)) ds.$$

Also, the reachable set of (2) satisfies

$$\text{vol}(\xi_\sigma(t, K)) \geq e^{\gamma_\sigma(t)} \text{vol}(K) \quad \forall t \geq 0 \quad (57)$$

with

$$\gamma_\sigma(t) := \min_{v \in K} \sum_{p \in \mathcal{P}} \int_0^t \text{tr}(J_x f_p(\xi_\sigma(s, v))) \mathbb{1}_p(\sigma(s)) ds.$$

Note that  $\bar{\eta}_\sigma(t)$  and  $\gamma_\sigma(t)$  are defined in terms of integrals of the matrix measure and trace of Jacobian matrix of the active mode over  $[0, t]$ , respectively, rewritten via the following observation: For a family of functions  $a_p : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}$  with  $p \in \mathcal{P}$ , we have

$$\int_0^t a_{\sigma(s)}(s) ds = \sum_{p \in \mathcal{P}} \int_0^t a_p(s) \mathbb{1}_p(\sigma(s)) ds. \quad (58)$$

The upper bound (56) extends a similar upper bound in [40, Th. 1] to the case of noncontractive switched systems and also an upper bound in the proof of [6, Th. 4.2] to the case of switched systems without a compact invariant set. Its proof is inspired by the variational constructions in the proofs of [40, Th. 1] and [6, Th. 4.2].

The following result provides alternative upper and lower bounds for the distance between two solutions to (2).

**Lemma 5** For all initial states  $x, \bar{x} \in K$ , the corresponding solutions to the switched system (2) satisfy

$$e^{\underline{\eta}_\sigma(t)} |\bar{x} - x| \leq |\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| \leq e^{\bar{\eta}_\sigma^{\text{alt}}(t)} |\bar{x} - x| \quad \forall t \geq 0 \quad (59)$$

with

$$\begin{aligned} \underline{\eta}_\sigma(t) &:= \sum_{p \in \mathcal{P}} \int_0^t \left( \min_{v \in \text{co}(\xi_\sigma(s, K))} -\mu(-J_x f_p(v)) \right) \mathbb{1}_p(\sigma(s)) ds, \\ \bar{\eta}_\sigma^{\text{alt}}(t) &:= \sum_{p \in \mathcal{P}} \int_0^t \left( \max_{v \in \text{co}(\xi_\sigma(s, K))} \mu(J_x f_p(v)) \right) \mathbb{1}_p(\sigma(s)) ds. \end{aligned}$$

Lemma 5 extends similar upper and lower bounds in [44, Th. 2.5.22, p.52] by taking the maximum and minimum over only the convex hull of reachable set instead of the entire state space in  $\underline{\eta}_\sigma(t)$  and  $\bar{\eta}_\sigma^{\text{alt}}(t)$ , respectively. Its proof is inspired by the variational construction in [44, Sect. 2.5] and is similar to the proof of the upper bound (56) in Lemma 4.<sup>6</sup>

The results in Lemmas 4 and 5 are compared in Remark 7.

- Remark 7** 1. The upper bound (56) and the one given by the second inequality in (59) are both useful in the sense that neither is less conservative, in part because the relation between the sets  $\xi_\sigma(t, \text{co}(K))$  and  $\text{co}(\xi_\sigma(t, K))$  is undetermined for nonlinear systems. However, (56) is less conservative or equivalent if the initial set  $K$  is convex, or if all modes of (2) are linear, as  $\xi_\sigma(t, \text{co}(K)) \subset \text{co}(\xi_\sigma(t, K))$  for the former case and  $\xi_\sigma(t, \text{co}(K)) = \text{co}(\xi_\sigma(t, K))$  for the latter, and the maximum is a subadditive function. All upper bounds for topological entropy in this paper are constructed using (56), and alternative results can be obtained if the second inequality in (59) is used instead, that is, if terms in the form of  $\xi_\sigma(t, \text{co}(K))$  are replaced with the corresponding ones in the form of  $\text{co}(\xi_\sigma(t, K))$ .
2. The first inequality in (13) implies that  $\gamma_\sigma(t)$  in (57) and  $\underline{\eta}_\sigma(t)$  in (59) satisfy  $\gamma_\sigma(t) \geq n \underline{\eta}_\sigma(t)$  for all  $t \geq 0$ . For this reason, volume-based arguments using (57) usually lead to less conservative lower bounds for entropy. However, the first inequality in (59) is useful for constructing a possibly less conservative lower bound for entropy in the case of block-diagonal structure in Sect. 4.2.

**Remark 8** When analyzing the exponential growth rate of the distance between two solutions to a nonlinear system, a measurable upper bound is often used in place of the matrix measure of Jacobian matrix in integrations over time. For example, in [44, Th. 2.5.22, p.52], the author used a measurable function  $\alpha(t) \geq \mu(J_x f(t, x))$  for all  $t \geq 0$  and  $x \in \mathbb{R}^n$ , and in [30, Th. 1], the authors used a measurable function  $\alpha(t) \geq \mu_{\chi(t)}(J_x f(x, \sigma(t)))$  for all  $t$  that are not switches and  $x$  in a set  $C$ . In this paper, the matrix measures and traces of Jacobian matrices are used directly in integrations over time, as they can be shown to be locally integrable in time under the assumptions in Sect. 2. Even for switched systems in which the Jacobian matrices are not locally integrable in time, one can still follow the analysis in this paper with trivial modifications (i.e., replacing the matrix measures and traces of Jacobian matrices with suitable integrable bounds) to obtain similar bounds for exponential growth rates and thus similar bounds for topological entropy.

## 6.2 Universal spanning and separated sets

Given a time horizon  $T \geq 0$  and a radius  $\varepsilon > 0$ , we provide a universal construction of  $(T, \varepsilon)$ -spanning and  $(T, \varepsilon)$ -separated sets by extending a notion of grid from [50]. For a vector  $\theta = (\theta_1, \dots, \theta_n) \in \mathbb{R}_{>0}^n$  which may depend on  $T$  and  $\varepsilon$ , we define the

<sup>6</sup> As shown in “Appendix A,” their main difference is that, in the proof of Lemma 5, the variational arguments are applied to the line segment connecting two solutions instead of the one connecting two initial states, which results in the different locations of convex hulls in, e.g.,  $\bar{\eta}_\sigma(t)$  and  $\bar{\eta}_\sigma^{\text{alt}}(t)$ .

following grid on the initial set  $K$ :<sup>7</sup>

$$G(\theta) := \{(k_1\theta_1, \dots, k_n\theta_n) \in K : k_1, \dots, k_n \in \mathbb{Z}\}. \quad (60)$$

As  $K$  is a compact set with nonempty interior, there exist closed hypercubes  $B_1$  with radius  $r_1 > 0$  and  $B_2$  with radius  $r_2 > 0$  such that  $B_1 \subset K \subset B_2$ . Then the cardinality of the grid  $G(\theta)$  satisfies

$$\prod_{i=1}^n \left\lfloor \frac{2r_1}{\theta_i} \right\rfloor \leq \#G(\theta) \leq \prod_{i=1}^n \left( \left\lfloor \frac{2r_2}{\theta_i} \right\rfloor + 1 \right).$$

For a point  $x = (x_1, \dots, x_n) \in G(\theta)$ , let  $R(x)$  be the open hyperrectangle in  $\mathbb{R}^n$  with center  $x$  and sides  $2\theta_1, \dots, 2\theta_n$ , that is,

$$R(x) := \{\bar{x}_1, \dots, \bar{x}_n\} \in \mathbb{R}^n : |\bar{x}_1 - x_1| < \theta_1, \dots, |\bar{x}_n - x_n| < \theta_n. \quad (61)$$

Then the points in  $G(\theta)$  adjacent to  $x$  are on the boundary of  $R(x)$ , and the union of all  $R(x)$  covers  $K$ , that is,

$$K \subset \bigcup_{x \in G(\theta)} R(x).$$

Comparing the hyperrectangle  $R(x)$  to the open ball  $B_{f_\sigma}(x, \varepsilon, T)$  defined by (3), we obtain the following result; the proof can be found in “Appendix B.”

**Lemma 6** 1. *If the vector  $\theta$  is selected so that*

$$R(x) \subset B_{f_\sigma}(x, \varepsilon, T) \quad \forall x \in G(\theta), \quad (62)$$

*then the grid  $G(\theta)$  is  $(T, \varepsilon)$ -spanning. Moreover, if (62) holds for all  $T \geq 0$  and  $\varepsilon > 0$ , and*

$$\limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\log \theta_i}{T} \leq 0 \quad \forall i \in \{1, \dots, n\}, \quad (63)$$

*then the topological entropy of the switched system (2) is upper bounded by*

$$h(f_\sigma, K) \leq \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(1/\theta_i)}{T}. \quad (64)$$

<sup>7</sup> In our construction we ignore the case when  $(K)$  falls between integer multiples of  $(\theta)$ , but if that happens then the construction can be slightly modified by taking an arbitrary  $(\bar{x} \in K)$  and defining the grid by  $(G(\theta) := \{\bar{x} + (k_1\theta_1, \dots, k_n\theta_n) \in K : k_1, \dots, k_n \in \mathbb{Z}\})$  so that it is nonempty.

2. If the vector  $\theta$  is selected so that

$$B_{f_\sigma}(x, \varepsilon, T) \subset R(x) \quad \forall x \in G(\theta), \quad (65)$$

then the grid  $G(\theta)$  is  $(T, \varepsilon)$ -separated. Moreover, if (65) holds for all  $T \geq 0$  and  $\varepsilon > 0$ , then the topological entropy of the switched system (2) is lower bounded by

$$h(f_\sigma, K) \geq \liminf_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(1/\theta_i)}{T}. \quad (66)$$

Lemma 6 extends [50, Lemma 2] to the case of nonlinear modes. Note that (63) is satisfied if all  $\theta_i$  are nonincreasing in  $T$ .<sup>8</sup>

### 6.3 Asymptotic weighted averages

Given a switching signal  $\sigma$ , consider the active times  $\tau_p(t)$  defined by (8), active rates  $\rho_p(t)$  defined by (9), and sets of persistent and strongly persistent modes  $\mathcal{P}_\infty$  and  $\mathcal{P}_\infty^+$  defined by (11). It was shown in [50, Lemma 1] that, for a family of constants  $c_p \in \mathbb{R}$  with  $p \in \mathcal{P}$ , we have

$$\limsup_{T \rightarrow \infty} \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} c_p \tau_p(t) = \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}} c_p \rho_p(t), 0 \right\}. \quad (67)$$

In this subsection, we present similar results for a case where the constants are replaced by locally (Lebesgue) integrable functions; the proof can be found in “Appendix C.”

**Lemma 7** Consider a family of locally integrable functions  $a_p^i : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}$  with  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}$ .

1. Let

$$\hat{a}_p^i := \limsup_{t \rightarrow \infty; \sigma(t)=p} a_p^i(t), \quad i \in \{1, \dots, m\}, p \in \mathcal{P}.$$

If the constants  $\hat{a}_p^i$  are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then

$$\begin{aligned} & \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} \int_0^t a_p^i(s) \mathbb{1}_p(\sigma(s)) ds \\ & \leq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} \hat{a}_p^i \tau_p(t). \end{aligned} \quad (68)$$

<sup>8</sup> Also, the lower bound (66) does not require a condition similar to (63). For this reason, in [51, Lemma 2.3] the requirement that all  $\theta_i$  are nonincreasing in  $T$  is not actually needed for the lower bound [51, eq. (13)].

2. Let

$$\check{a}_p^i := \liminf_{t \rightarrow \infty: \sigma(t)=p} a_p^i(t), \quad i \in \{1, \dots, m\}, p \in \mathcal{P}.$$

If the constants  $\check{a}_p^i$  are finite for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , then

$$\begin{aligned} \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} \int_0^t a_p^i(s) \mathbb{1}_p(\sigma(s)) ds \\ \geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} \check{a}_p^i \tau_p(t) \end{aligned} \quad (69)$$

and

$$\begin{aligned} \limsup_{t \rightarrow \infty} \sum_{i=1}^m \max \left\{ \frac{1}{t} \sum_{p \in \mathcal{P}} \int_0^t a_p^i(s) \mathbb{1}_p(\sigma(s)) ds, 0 \right\} \\ \geq \limsup_{t \rightarrow \infty} \sum_{i=1}^m \max \left\{ \sum_{p \in \mathcal{P}_\infty^+} \check{a}_p^i \rho_p(t), 0 \right\}. \end{aligned} \quad (70)$$

**Remark 9** The inequalities (68)–(70) can be extended to some cases where the functions  $a_p^i$  are locally integrable but possibly unbounded. For example, (69) still holds if for all  $i \in \{1, \dots, m\}$ , we have  $\check{a}_p^i \in \mathbb{R} \cup \{+\infty\}$  for all  $p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+$  and  $\check{a}_p^i \in \mathbb{R}$  for all  $p \in \mathcal{P}_\infty^+$ . Moreover, if  $\check{a}_p^i \in \mathbb{R} \cup \{+\infty\}$  for all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , and there exist  $j \in \{1, \dots, m\}$  and  $q \in \mathcal{P}_\infty^+$  such that  $\check{a}_q^j = +\infty$ , then

$$\limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} \int_0^t a_p^i(s) \mathbb{1}_p(\sigma(s)) ds = +\infty.$$

The proofs are along the lines of that of Lemma 7 and thus omitted here. Similar extensions can be made for the inequalities (68) and (70), and consequently all bounds for entropy of switched systems in this paper.

For a family of constants  $c_p \in \mathbb{R}$  with  $p \in \mathcal{P}$ , the equality (67) can be improved using arguments similar to those in the first two steps of the proof of Lemma 7, which leads to the following result:

$$\begin{aligned} \limsup_{T \rightarrow \infty} \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} c_p \tau_p(t) &= \limsup_{T \rightarrow \infty} \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} c_p \tau_p(t) \\ &= \max \left\{ \limsup_{t \rightarrow \infty} \sum_{p \in \mathcal{P}_\infty^+} c_p \rho_p(t), 0 \right\}. \end{aligned} \quad (71)$$

## 6.4 Proof of Theorem 3

We prove only the upper bound (39) here; the lower bound (41) can be established using similar arguments (the omitted proof can be found in [52]). By applying the upper bound for the distance between two solutions (56) to each subsystem of (37) with the corresponding “local” norm and matrix measure, we obtain that, for all initial states  $x = (x_1, \dots, x_m)$ ,  $\bar{x} = (\bar{x}_1, \dots, \bar{x}_m) \in K$  with  $x_i, \bar{x}_i \in \mathbb{R}^{n_i}$  for  $i \in \{1, \dots, m\}$ , the corresponding solutions satisfy

$$|\xi_\sigma^i(t, \bar{x}_i) - \xi_\sigma^i(t, x_i)|_i \leq e^{\bar{\eta}_\sigma^i(t)} |\bar{x}_i - x_i|_i \quad \forall i \in \{1, \dots, m\}, t \geq 0$$

with

$$\bar{\eta}_\sigma^i(t) := \max_{v_i \in \text{co}(K_i)} \sum_{p \in \mathcal{P}} \int_0^t \mu_i(J_{x_i} f_p^i(\xi_\sigma^i(s, v_i)) \mathbb{1}_p(\sigma(s))) ds.$$

Due to the equivalence of norms on a finite-dimensional vector space, there exist constants  $r_1, \dots, r_m, r_N > 0$  such that

$$|v_i|_i \leq r_i |v_i|_\infty \quad \forall i \in \{1, \dots, m\}, v_i \in \mathbb{R}^{n_i}$$

and

$$|v|_N \leq r_N |v|_\infty \quad \forall v \in \mathbb{R}^m.$$

Then the definition of the “global” norm (24) implies that

$$\begin{aligned} |\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)|_G &\leq \max_{1 \leq i \leq m} r_N |\xi_\sigma^i(t, \bar{x}_i) - \xi_\sigma^i(t, x_i)|_i \\ &\leq \max_{1 \leq i \leq m} e^{\bar{\eta}_\sigma^i(t)} r_N |\bar{x}_i - x_i|_i \leq \max_{1 \leq i \leq m} e^{\bar{\eta}_\sigma^i(t)} r_N r_i |\bar{x}_i - x_i|_\infty \end{aligned}$$

for all  $t \geq 0$ . Consequently, given arbitrary time horizon  $T \geq 0$  and radius  $\varepsilon > 0$ , we have

$$\max_{t \in [0, T]} |\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)|_G \leq \max_{1 \leq i \leq m} e^{\max_{t \in [0, T]} \bar{\eta}_\sigma^i(t)} r_N r_i |\bar{x}_i - x_i|_\infty. \quad (72)$$

Consider the grid  $G(\theta)$  defined by (60) with the vector  $\theta = (\theta_1 \mathbf{1}_{n_1}, \dots, \theta_m \mathbf{1}_{n_m}) \in \mathbb{R}_{>0}^n$  defined by

$$\theta_i := e^{-\max_{t \in [0, T]} \bar{\eta}_\sigma^i(t)} \varepsilon / (r_N r_i), \quad i \in \{1, \dots, m\}.$$

Comparing the corresponding hyperrectangles  $R(x)$  defined by (61) to the open balls  $B_{f_\sigma}(x, \varepsilon, T)$  defined by (3) with the “global” norm  $|\cdot|_G$ , we see that (72) implies  $R(x) \subset B_{f_\sigma}(x, \varepsilon, T)$  for all  $x \in G(\theta)$ . Then part 1 of Lemma 6 implies that  $G(\theta)$  is

$(T, \varepsilon)$ -spanning. As  $T \geq 0$  and  $\varepsilon > 0$  are arbitrary, and all  $\theta_i$  are nonincreasing in  $T$ , the upper bound (64) implies that

$$\begin{aligned} h(f_\sigma, K) &\leq \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{n_i \log(1/\theta_i)}{T} \\ &= \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} n_i \bar{\eta}_\sigma^i(t) + \lim_{\varepsilon \searrow 0} \lim_{T \rightarrow \infty} \sum_{i=1}^m \frac{n_i \log(r_N r_i / \varepsilon)}{T} \\ &\leq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} \int_0^t \left( \max_{\bar{v}_i \in \xi_\sigma^i(s, \text{co}(K_i))} n_i \mu_i(J_{x_i} f_p^i(\bar{v}_i)) \right) \mathbb{1}_p(\sigma(s)) ds, \end{aligned}$$

where the last inequality holds in part because the maximum is a subadditive function. Finally, we obtain (39) by invoking the upper bound (68) with the functions

$$a_p^i(t) = \max_{\bar{v}_i \in \xi_\sigma^i(t, \text{co}(K_i))} n_i \mu_i(J_{x_i} f_p^i(\bar{v}_i)), \quad i \in \{1, \dots, m\}, \quad p \in \mathcal{P}.$$

□

## 6.5 Proof of Theorem 4

We prove the lower bound (43) using volume-based arguments. As  $K$  is a compact set with nonempty interior, there exists a hyperrectangle  $R = R_1 \times \dots \times R_m$  with  $R_i \subset K_i$  for  $i \in \{1, \dots, m\}$ . Then  $R \subset K$  and

$$\xi_\sigma(t, R) = \xi_\sigma^1(t, R_1) \times \dots \times \xi_\sigma^m(t, R_m) \quad \forall t \geq 0$$

for the switched block-diagonal system (37).

Given arbitrary time horizon  $T \geq 0$  and radius  $\varepsilon > 0$ , by applying the lower bound for the volume of reachable set (57) to each subsystem of (37), we obtain that

$$\text{vol}(\xi_\sigma^i(T, R_i)) \geq e^{\gamma_\sigma^i(T)} \text{vol}(R_i) \quad \forall i \in \{1, \dots, m\}$$

with (recall that  $R_i \subset K_i$ )

$$\gamma_\sigma^i(t) := \min_{v_i \in K_i} \sum_{p \in \mathcal{P}} \int_0^t \text{tr}(J_{x_i} f_p^i(\xi_\sigma^i(s, v_i))) \mathbb{1}_p(\sigma(s)) ds.$$

Let  $\mathcal{I} = \{i_1, \dots, i_l\} := \{i : \gamma_\sigma^i(T) > 0\}$  which depends on  $T$ , and define

$$\xi_\sigma^{\mathcal{I}}(T, R_{\mathcal{I}}) := \xi_\sigma^{i_1}(T, R_{i_1}) \times \dots \times \xi_\sigma^{i_l}(T, R_{i_l}).$$



Then

$$\begin{aligned} \text{vol}(\xi_{\sigma}^{\mathcal{I}}(T, R_{\mathcal{I}})) &= \prod_{i \in \mathcal{I}} \text{vol}(\xi_{\sigma}^i(T, R_i)) \geq e^{\sum_{i \in \mathcal{I}} \gamma_{\sigma}^i(T)} \prod_{i \in \mathcal{I}} \text{vol}(R_i) \\ &\geq e^{\sum_{i=1}^m \max\{\gamma_{\sigma}^i(T), 0\}} \prod_{i=1}^m \min\{\text{vol}(R_i), 1\}. \end{aligned} \quad (73)$$

Let  $E$  be a minimal  $(T, \varepsilon)$ -spanning set defined by (3) and (4) with the “global” norm  $|\cdot|_G$ . Due to the equivalence of norms on a finite-dimensional vector space, there exist constants  $\bar{r}_1, \dots, \bar{r}_m, \bar{r}_N > 0$  such that

$$|v_i|_{\infty} \leq \bar{r}_i |v_i| \quad \forall i \in \{1, \dots, m\}, \quad v_i \in \mathbb{R}^{n_i}$$

and

$$|v|_{\infty} \leq \bar{r}_N |v|_N \quad \forall v \in \mathbb{R}^m.$$

Then for all initial states  $x = (x_1, \dots, x_m), \bar{x} = (\bar{x}_1, \dots, \bar{x}_m) \in \mathbb{R}^n$  with  $x_i, \bar{x}_i \in \mathbb{R}^{n_i}$  for  $i \in \{1, \dots, m\}$ , the definition of the “global” norm (24) implies that

$$\begin{aligned} |\xi_{\sigma}(T, \bar{x}) - \xi_{\sigma}(T, x)|_G &\geq \max_{1 \leq i \leq m} |\xi_{\sigma}^i(T, \bar{x}_i) - \xi_{\sigma}^i(T, x_i)| / \bar{r}_N \\ &\geq \max_{1 \leq i \leq m} |\xi_{\sigma}^i(T, \bar{x}_i) - \xi_{\sigma}^i(T, x_i)|_{\infty} / (\bar{r}_N \bar{r}_i). \end{aligned}$$

Hence, for the set  $\mathcal{I} = \{i_1, \dots, i_l\}$ , we have (recall that  $R \subset K$ )

$$\begin{aligned} \xi_{\sigma}^{\mathcal{I}}(T, R_{\mathcal{I}}) &\subset \{(\xi_{\sigma}^{i_1}(T, \bar{x}_{i_1}), \dots, \xi_{\sigma}^{i_l}(T, \bar{x}_{i_l})) : (\bar{x}_1, \dots, \bar{x}_m) \in K\} \\ &\subset \bigcup_{x \in E} \{(\xi_{\sigma}^{i_1}(T, \bar{x}_{i_1}), \dots, \xi_{\sigma}^{i_l}(T, \bar{x}_{i_l})) : |\xi_{\sigma}(T, (\bar{x}_1, \dots, \bar{x}_m)) - \xi_{\sigma}(T, x)|_G < \varepsilon\} \\ &\subset \bigcup_{(x_1, \dots, x_m) \in E} \{(v_{i_1}, \dots, v_{i_l}) : |v_i - \xi_{\sigma}^i(T, x_i)|_{\infty} < \bar{r}_N \bar{r}_i \varepsilon \text{ for all } i \in \mathcal{I}\}, \end{aligned}$$

and thus,

$$\text{vol}(\xi_{\sigma}^{\mathcal{I}}(T, R_{\mathcal{I}})) \leq \#E \prod_{i \in \mathcal{I}} (2\bar{r}_N \bar{r}_i \varepsilon)^{n_i} \leq \#E \prod_{i=1}^m \max\{(2\bar{r}_N \bar{r}_i \varepsilon)^{n_i}, 1\}. \quad (74)$$

Combining (73) and (74), we obtain that the minimal cardinality of a  $(T, \varepsilon)$ -spanning set satisfies

$$S(f_{\sigma}, \varepsilon, T, K) = \#E \geq e^{\sum_{i=1}^m \max\{\gamma_{\sigma}^i(T), 0\}} \prod_{i=1}^m \frac{\min\{\text{vol}(R_i), 1\}}{\max\{(2\bar{r}_N \bar{r}_i \varepsilon)^{n_i}, 1\}}.$$

Hence, the definition of entropy (5) implies that

$$\begin{aligned} h(f_\sigma, K) &\geq \liminf_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{1}{T} \log \left( e^{\sum_{i=1}^m \max\{\gamma_\sigma^i(T), 0\}} \prod_{i=1}^m \frac{\min\{\text{vol}(R_i), 1\}}{\max\{(2r_N r_i \varepsilon)^{n_i}, 1\}} \right) \\ &= \limsup_{T \rightarrow \infty} \sum_{i=1}^m \max \left\{ \frac{\gamma_\sigma^i(T)}{T}, 0 \right\} + \lim_{\varepsilon \searrow 0} \lim_{T \rightarrow \infty} \frac{1}{T} \sum_{i=1}^m \log \left( \frac{\min\{\text{vol}(R_i), 1\}}{\max\{(2r_N r_i \varepsilon)^{n_i}, 1\}} \right) \\ &\geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \max \left\{ \frac{1}{T} \sum_{p \in \mathcal{P}} \int_0^T \left( \min_{\tilde{v}_i \in \xi_\sigma^i(s, K_i)} \text{tr}(J_{x_i} f_p^i(\tilde{v}_i)) \right) \mathbb{1}_p(\sigma(s)) ds, 0 \right\}, \end{aligned}$$

where the last inequality holds in part because the minimum is a superadditive function. Finally, we obtain (43) by invoking the lower bound (70) with the functions

$$a_p^i(t) = \min_{\tilde{v}_i \in \xi_\sigma^i(t, K_i)} \text{tr}(J_{x_i} f_p^i(\tilde{v}_i)), \quad i \in \{1, \dots, m\}, \quad p \in \mathcal{P}.$$

□

## 6.6 Proof of Theorem 1

Note that the switched system (2) can be seen as a switched block-diagonal system (37) with a single block. Consequently, the upper bound (17) and lower bound (19) for the entropy of (2) can be obtained by taking  $m = 1$  and  $n_1 = n$  in the upper bound (44) and lower bound (43) for the entropy of (37), respectively. For a stand-alone proof of slightly weaker results (without considering persistent and strongly persistent modes), see the proof of [51, Th. 3.1]. □

## 7 Conclusion

Upper and lower bounds for topological entropy of switched nonlinear and interconnected systems were constructed, which generalized and extended previous results on switched linear systems and advanced our understanding of the effects of switching on topological entropy. A feature of these bounds is that they depend on the values of Jacobian matrices of only strongly persistent modes and over only an  $\omega$ -limit set. As a result, they are easier to compute and are able to yield finite bounds in the case of unbounded Jacobian matrices but a compact global attractor.

Future research directions include analyzing the computation complexities of the bounds for topological entropy in this paper, investigating the relations between these bounds and stability conditions for switched nonlinear and interconnected systems, and constructing bounds for topological entropy of switched nonlinear systems with triangular structure and general time-varying systems.

**Acknowledgements** This work was supported in part by the National Science Foundation Grant CMMI-2106043 and in part by the National Science Foundation Grant EPCN-1608880.

## Appendix A Proofs of Lemmas 4 and 5

Lemmas 4 and 5 are established based on similar properties of a linear time-varying (LTV) system

$$\dot{x} = A(t)x \quad (\text{A1})$$

with a piecewise-continuous, matrix-valued function  $A : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}^{n \times n}$ . The solution to (A1) at time  $t \geq 0$  with initial state  $v$  is given by  $\xi(t, v) = \Phi_A(t, 0)v$ , where  $\Phi_A(t, 0)$  is the state-transition matrix and satisfies Coppel's inequalities [14, Th. 2.8.27, p. 34]

$$e^{\int_0^t -\mu(-A(s))ds} |v| \leq |\Phi_A(t, 0)v| \leq e^{\int_0^t \mu(A(s))ds} |v| \quad \forall t \geq 0, v \in \mathbb{R}^n \quad (\text{A2})$$

and Liouville's formula [9, Th. 4.1, p. 28]

$$\det(\Phi_A(t, 0)) = e^{\int_0^t \text{tr}(A(s))ds} \quad \forall t \geq 0. \quad (\text{A3})$$

**Proof of Lemma 4** We prove Lemma 4 by writing the Jacobian matrix of a solution to the switched nonlinear system (2) with respect to initial state  $J_x \xi_\sigma(t, x)$  as a matrix solution to the LTV system (A1) with a suitable function  $A(t)$ , using variational arguments from nonlinear systems analysis (see, e.g., [24, Sect. 4.2.4]). For all  $v \in \mathbb{R}^n$ , we have  $J_x \xi_\sigma(0, v) = I$  and

$$\partial_t J_x \xi_\sigma(t, v) = J_x \dot{\xi}_\sigma(t, v) = J_x f_{\sigma(t)}(\xi_\sigma(t, v)) J_x \xi_\sigma(t, v)$$

for all  $t \geq 0$  that are not switches. Hence, for each fixed  $v \in \mathbb{R}^n$ , the matrix  $J_x \xi_\sigma(t, v)$  is equal to the state-transition matrix  $\Phi_A(t, 0)$  of (A1) with  $A(t) = J_x f_{\sigma(t)}(\xi_\sigma(t, v))$ .

First, given arbitrary initial states  $x, \bar{x} \in K$ , let

$$v(\rho) := \rho \bar{x} + (1 - \rho)x, \quad \rho \in [0, 1].$$

Then  $v(\rho) \in \text{co}(K)$  and  $v'(\rho) = \bar{x} - x$  for all  $\rho \in [0, 1]$ . Hence,

$$\begin{aligned} & |\xi_\sigma(t, \bar{x}) - \xi_\sigma(t, x)| \\ &= |\xi_\sigma(t, v(1)) - \xi_\sigma(t, v(0))| = \left| \int_0^1 J_x \xi_\sigma(t, v(\rho))(\bar{x} - x) d\rho \right| \\ &\leq \int_0^1 |J_x \xi_\sigma(t, v(\rho))(\bar{x} - x)| d\rho \leq \int_0^1 e^{\int_0^t \mu(J_x f_{\sigma(s)}(\xi_\sigma(s, v(\rho)))) ds} |\bar{x} - x| d\rho \\ &\leq \left( \max_{v \in \text{co}(K)} e^{\int_0^t \mu(J_x f_{\sigma(s)}(\xi_\sigma(s, v)))) ds} \right) |\bar{x} - x| = e^{\bar{\eta}_\sigma(t)} |\bar{x} - x| \end{aligned}$$

for all  $t \geq 0$ , where the second inequality follows from the second inequality in (A2) with  $A(t) = J_x f_{\sigma(t)}(\xi_\sigma(t, v(\rho)))$  and  $\Phi_A(t, 0) = J_x \xi_\sigma(t, v(\rho))$ , and the last equality follows from the transformation (58). Hence, (56) holds.

Second, for each fixed  $v \in \mathbb{R}^n$ , Liouville's formula (A3) with  $A(t) = J_x f_{\sigma(t)}(\xi_{\sigma}(t, v))$  and  $\Phi_A(t, 0) = J_x \xi_{\sigma}(t, v)$  implies that

$$\det(J_x \xi_{\sigma}(t, v)) = e^{\int_0^t \text{tr}(J_x f_{\sigma(s)}(\xi_{\sigma}(s, v))) ds} \quad \forall t \geq 0.$$

Then

$$\begin{aligned} \text{vol}(\xi_{\sigma}(t, K)) &= \int_K |\det(J_x \xi_{\sigma}(t, v))| dv \geq \left( \min_{v \in K} |\det(J_x \xi_{\sigma}(t, v))| \right) \text{vol}(K) \\ &= \left( \min_{v \in K} e^{\int_0^t \text{tr}(J_x f_{\sigma(s)}(\xi_{\sigma}(s, v))) ds} \right) \text{vol}(K) = e^{\gamma_{\sigma}(t)} \text{vol}(K) \end{aligned}$$

for all  $t \geq 0$ , where the last equality follows from the transformation (58). Hence, (57) holds.  $\square$

**Proof of Lemma 5** We prove Lemma 5 by writing the difference between two solutions to the switched nonlinear system (2) as a solution to the LTV system (A1) with a suitable function  $A(t)$ , using variational arguments similar to those in the proof of Lemma 4. Given arbitrary initial states  $x, \bar{x} \in K$ , let

$$v(t, \rho) := \rho \xi_{\sigma}(t, \bar{x}) + (1 - \rho) \xi_{\sigma}(t, x), \quad \rho \in [0, 1], t \geq 0.$$

Then  $v(t, \rho) \in \text{co}(\xi_{\sigma}(t, K))$  and  $\partial_{\rho} v(t, \rho) = \xi_{\sigma}(t, \bar{x}) - \xi_{\sigma}(t, x)$  for all  $\rho \in [0, 1]$  and  $t \geq 0$ . Hence,

$$\begin{aligned} \partial_t (\xi_{\sigma}(t, \bar{x}) - \xi_{\sigma}(t, x)) &= f_{\sigma(t)}(\xi_{\sigma}(t, \bar{x})) - f_{\sigma(t)}(\xi_{\sigma}(t, x)) \\ &= f_{\sigma(t)}(v(t, 1)) - f_{\sigma(t)}(v(t, 0)) \\ &= \left( \int_0^1 J_x f_{\sigma(t)}(v(t, \rho)) d\rho \right) (\xi_{\sigma}(t, \bar{x}) - \xi_{\sigma}(t, x)) \end{aligned}$$

for all  $t \geq 0$  that are not switches. Therefore,  $\xi_{\sigma}(t, \bar{x}) - \xi_{\sigma}(t, x)$  is the solution to (A1) with  $A(t) = \int_0^1 J_x f_{\sigma(t)}(v(t, \rho)) d\rho$  at time  $t$  with initial state  $\bar{x} - x$ . Consequently, (A2) implies that

$$\begin{aligned} e^{\int_0^t -\mu\left(-\int_0^1 J_x f_{\sigma(s)}(v(s, \rho)) d\rho\right) ds} |\bar{x} - x| &\leq |\xi_{\sigma}(t, \bar{x}) - \xi_{\sigma}(t, x)| \\ &\leq e^{\int_0^t \mu\left(\int_0^1 J_x f_{\sigma(s)}(v(s, \rho)) d\rho\right) ds} |\bar{x} - x| \end{aligned}$$

for all  $t \geq 0$ . Moreover, as the matrix measure  $\mu$  is a convex function, Jensen's inequality [3, Th. 11.24, p.417] implies that

$$\begin{aligned} \mu\left(\int_0^1 J_x f_{\sigma(t)}(v(t, \rho)) d\rho\right) &\leq \int_0^1 \mu(J_x f_{\sigma(t)}(v(t, \rho)) d\rho \\ &\leq \max_{v \in \text{co}(\xi_{\sigma}(t, K))} \mu(J_x f_{\sigma(t)}(v)) \end{aligned}$$

and

$$\begin{aligned} -\mu\left(-\int_0^1 J_x f_{\sigma(t)}(v(t, \rho)) d\rho\right) &\geq \int_0^1 -\mu(-J_x f_{\sigma(t)}(v(t, \rho)) d\rho \\ &\geq \min_{v \in \text{co}(\xi_{\sigma}(t, K))} -\mu(-J_x f_{\sigma(t)}(v)) \end{aligned}$$

for all  $t \geq 0$ . Then (59) follows from the transformation (58).  $\square$

## Appendix B Proof of Lemma 6

1. If (62) holds, then

$$K \subset \bigcup_{x \in G(\theta)} R(x) \subset \bigcup_{x \in G(\theta)} B_{f_{\sigma}}(x, \varepsilon, T).$$

Hence,  $G(\theta)$  is  $(T, \varepsilon)$ -spanning following the definition (4), and thus,

$$S(f_{\sigma}, \varepsilon, T, K) \leq \#G(\theta) \leq \prod_{i=1}^n \left( \left\lfloor \frac{2r_2}{\theta_i} \right\rfloor + 1 \right) \leq \prod_{i=1}^n \left( \frac{2r_2}{\theta_i} + 1 \right).$$

If (62) holds for all  $T \geq 0$  and  $\varepsilon > 0$ , then the definition of entropy (5) implies that

$$\begin{aligned} h(f_{\sigma}, K) &\leq \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(2r_2/\theta_i + 1)}{T} \\ &\leq \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(1/\theta_i)}{T} \\ &\quad + \sum_{i=1}^n \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\log(\theta_i + 2r_2)}{T}, \end{aligned} \quad (\text{B4})$$

where the last inequality holds as the upper limit is a subadditive function. Moreover, for all  $i \in \{1, \dots, n\}$ , the summands in the last term in (B4) satisfy

$$\begin{aligned}
\limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\log(\theta_i + 2r_2)}{T} &\leq \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\max\{\log(2\theta_i), \log(4r_2)\}}{T} \\
&= \max \left\{ \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\log(2\theta_i)}{T}, \lim_{T \rightarrow \infty} \frac{\log(4r_2)}{T} \right\} \\
&= \max \left\{ \limsup_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \frac{\log \theta_i}{T}, 0 \right\},
\end{aligned}$$

where the inequality holds as the logarithm is an increasing function and  $\theta_i, r_2 > 0$ , and the last equality holds in part because  $r_2$  is independent of  $T$ . Then (63) implies (64).<sup>9</sup>

2. If (65) holds, then for all distinct points  $x, \bar{x} \in G(\theta)$ , we have  $\bar{x} \notin B_{f_\sigma}(x, \varepsilon, T)$  as  $\bar{x} \notin R(x)$ . Hence,  $G(\theta)$  is  $(T, \varepsilon)$ -separated following the definition (6), and thus,

$$N(f_\sigma, \varepsilon, T, K) \geq \#G(\theta) \geq \prod_{i=1}^n \left\lfloor \frac{2r_1}{\theta_i} \right\rfloor \geq \prod_{i=1}^n \max \left\{ \frac{2r_1}{\theta_i} - 1, 1 \right\}.$$

If (65) holds for all  $T \geq 0$  and  $\varepsilon > 0$ , then the alternative definition of entropy (7) implies that

$$\begin{aligned}
h(f_\sigma, K) &\geq \liminf_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(\max\{2r_1/\theta_i - 1, 1\})}{T} \\
&\geq \liminf_{\varepsilon \searrow 0} \limsup_{T \rightarrow \infty} \sum_{i=1}^n \frac{\log(1/\theta_i)}{T} \\
&\quad + \sum_{i=1}^n \liminf_{\varepsilon \searrow 0} \liminf_{T \rightarrow \infty} \frac{\log(\max\{2r_1 - \theta_i, \theta_i\})}{T}, \quad (\text{B5})
\end{aligned}$$

where the last inequality holds as the lower limit is a superadditive function, and for two functions  $g, \bar{g} : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}$ , we have

$$\limsup_{T \rightarrow \infty} (g(T) + \bar{g}(T)) \geq \limsup_{T \rightarrow \infty} g(T) + \liminf_{T \rightarrow \infty} \bar{g}(T).$$

Moreover, for all  $i \in \{1, \dots, n\}$ , the summands in the last term in (B5) satisfy

$$\begin{aligned}
\liminf_{\varepsilon \searrow 0} \liminf_{T \rightarrow \infty} \frac{\log(\max\{2r_1 - \theta_i, \theta_i\})}{T} &\geq \liminf_{\varepsilon \searrow 0} \liminf_{T \rightarrow \infty} \frac{\log(\max\{r_1, \theta_i\})}{T} \\
&\geq \liminf_{\varepsilon \searrow 0} \liminf_{T \rightarrow \infty} \frac{\log r_1}{T} = 0,
\end{aligned}$$

<sup>9</sup> There was a typo in [50, Lemma 2] where [50, eq. (17)] should be replaced with (63), as the inequality in (63) needs to hold for each  $i \in \{1, \dots, n\}$  instead of the upper limits of the sum.

where the first inequality holds as the logarithm is an increasing function and  $r_1, \theta_i > 0$ , and the equality holds as  $r_1$  is independent of  $T$ . Hence, (66) holds.  $\square$

## Appendix C Proof of Lemma 7

We prove only the lower bound (69) here; the upper bound (68) and lower bound (70) can be established using similar arguments (the omitted proof can be found in [52]). For brevity, we define the following functions on  $\mathbb{R}_{\geq 0}$ :

$$\begin{aligned}\eta_p^i(t) &:= \int_0^t a_p^i(s) \mathbb{1}_p(\sigma(s)) ds, \quad p \in \mathcal{P}, \\ \bar{a}^i(T) &:= \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}} \eta_p^i(t),\end{aligned} \quad i \in \{1, \dots, m\}$$

with  $\bar{a}^i(0) := \max\{a_{\sigma(0)}^i(0), 0\}$ . Also, note that for two continuous functions  $g, \bar{g} : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}$ , we have

$$\max_{t \in [0, T]} (g(t) + \bar{g}(t)) \geq \max_{t \in [0, T]} g(t) + \min_{t \in [0, T]} \bar{g}(t) \quad \forall T \geq 0. \quad (\text{C6})$$

First, we eliminate modes that are not persistent. The definition of  $\mathcal{P}_\infty$  in (11) implies that  $t_\infty := \sup\{t \geq 0 : \sigma(t) \in \mathcal{P} \setminus \mathcal{P}_\infty\}$  is finite. Then

$$\begin{aligned}\bar{a}^i(T) &\geq \frac{1}{T} \left( \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty} \eta_p^i(t) + \min_{t \in [0, T]} \sum_{p \in \mathcal{P} \setminus \mathcal{P}_\infty} \eta_p^i(t) \right) \\ &= \frac{1}{T} \left( \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty} \eta_p^i(t) + \min_{t \in [0, t_\infty]} \sum_{p \in \mathcal{P} \setminus \mathcal{P}_\infty} \eta_p^i(t) \right)\end{aligned}$$

for all  $i \in \{1, \dots, m\}$  and  $T > t_\infty$ , where the inequality follows from (C6). Hence,

$$\limsup_{T \rightarrow \infty} \sum_{i=1}^m \bar{a}^i(T) \geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty} \eta_p^i(t).$$

Second, we eliminate modes that are persistent but not strongly persistent. For all  $i \in \{1, \dots, m\}$  and  $p \in \mathcal{P}_\infty$ , as  $\check{a}_p^i = \liminf_{t \rightarrow \infty : \sigma(t)=p} a_p^i(t)$  are finite,  $\check{\alpha}_p^i := \inf_{t \geq 0} a_p^i(t) \mathbb{1}_p(\sigma(t))$  are finite as well. Then

$$\begin{aligned}\frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty} \eta_p^i(t) &\geq \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} \eta_p^i(t) + \frac{1}{T} \min_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+} \eta_p^i(t) \\ &\geq \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} \eta_p^i(t) + \sum_{p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+} \min\{\check{\alpha}_p^i, 0\} \rho_p(T)\end{aligned}$$

for all  $i \in \{1, \dots, m\}$  and  $T > 0$ , where the first inequality follows from (C6). Moreover, for all  $p \notin \mathcal{P}_\infty^+$ , as  $\rho_p(t) \geq 0$  for all  $t \geq 0$  and  $\hat{\rho}_p = \limsup_{t \rightarrow \infty} \rho_p(t) = 0$ , we have  $\hat{\rho}_p = \lim_{t \rightarrow \infty} \rho_p(t) = 0$ . Then

$$\lim_{T \rightarrow \infty} \sum_{i=1}^m \sum_{p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+} \min\{\check{\alpha}_p^i, 0\} \rho_p(T) = \sum_{i=1}^m \sum_{p \in \mathcal{P}_\infty \setminus \mathcal{P}_\infty^+} \min\{\check{\alpha}_p^i, 0\} \hat{\rho}_p = 0.$$

Hence,

$$\limsup_{T \rightarrow \infty} \sum_{i=1}^m \bar{a}^i(T) \geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_\infty^+} \eta_p^i(t).$$

Finally, as  $\mathcal{P}_\infty^+$  is a finite set, the lower limit in the definition of  $\check{a}_p^i$  implies that, for each  $\delta > 0$ , there exists a large enough  $t_\delta \geq 0$  such that

$$a_p^i(t) > \check{a}_p^i - \delta \quad \forall i \in \{1, \dots, m\}, p \in \mathcal{P}_\infty^+, t > t_\delta : \sigma(t) = p.$$

For all  $i \in \{1, \dots, m\}$  and  $t \geq 0$ , consider

$$\begin{aligned} \sum_{p \in \mathcal{P}_\infty^+} \eta_p^i(t) &= \sum_{p \in \mathcal{P}_\infty^+} \int_0^t (a_p^i(s) - \check{a}_p^i + \delta + \check{a}_p^i - \delta) \mathbb{1}_p(\sigma(s)) ds \\ &= \sum_{p \in \mathcal{P}_\infty^+} \check{a}_p^i \tau_p(t) - \delta t + \sum_{p \in \mathcal{P}_\infty^+} \int_0^t (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds. \end{aligned}$$

If  $t > t_\delta$ , then

$$\sum_{p \in \mathcal{P}_\infty^+} \int_0^t (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds \geq \sum_{p \in \mathcal{P}_\infty^+} \int_0^{t_\delta} (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds.$$

Otherwise  $t \in [0, t_\delta]$ , and hence,

$$\begin{aligned} &\sum_{p \in \mathcal{P}_\infty^+} \int_0^t (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds \\ &\geq \min_{\bar{t} \in [0, t_\delta]} \sum_{p \in \mathcal{P}_\infty^+} \int_0^{\bar{t}} (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds. \end{aligned}$$

Combining the two cases, we obtain

$$\sum_{p \in \mathcal{P}_\infty^+} \eta_p^i(t) \geq \sum_{p \in \mathcal{P}_\infty^+} \check{a}_p^i \tau_p(t) - \delta t + \min_{\bar{t} \in [0, t_\delta]} \sum_{p \in \mathcal{P}_\infty^+} \int_0^{\bar{t}} (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds.$$



Then

$$\begin{aligned} \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_{\infty}^+} \eta_p^i(t) &\geq \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_{\infty}^+} \check{a}_p^i \tau_p(t) - \delta \\ &\quad + \frac{1}{T} \min_{\bar{t} \in [0, t_{\delta}]} \sum_{p \in \mathcal{P}_{\infty}^+} \int_0^{\bar{t}} (a_p^i(s) - \check{a}_p^i + \delta) \mathbb{1}_p(\sigma(s)) ds \end{aligned}$$

for all  $T > 0$ , where the inequality follows in part from (C6). Hence,

$$\limsup_{T \rightarrow \infty} \sum_{i=1}^m \bar{a}_i(T) \geq \limsup_{T \rightarrow \infty} \sum_{i=1}^m \frac{1}{T} \max_{t \in [0, T]} \sum_{p \in \mathcal{P}_{\infty}^+} \check{a}_p^i \tau_p(t) - m\delta.$$

Then (69) holds as  $\delta > 0$  is arbitrary.  $\square$

## References

- Adler RL, Konheim AG, McAndrew MH (1965) Topological entropy. *Trans Am Math Soc* 114(2):309–319
- Aleksandrov AY, Chen Y, Platonov AV et al (2011) Stability analysis for a class of switched nonlinear systems. *Automatica* 47(10):2286–2291
- Aliprantis CD, Border KC (2006) Infinite dimensional analysis. Springer, Berlin
- Berger GO, Jungers RM (2020) Worst-case topological entropy and minimal data rate for state observation of switched linear systems. In: 23rd International conference on hybrid systems: computation and control, Sydney, Australia
- Bernstein DS (2009) Matrix mathematics. Princeton University Press, Princeton
- Boichenko VA, Leonov GA (1998) Lyapunov's direct method in estimates of topological entropy. *J Math Sci* 91(6):3370–3379
- Bowen R (1971) Entropy for group endomorphisms and homogeneous spaces. *Trans Am Math Soc* 153:401–414
- Bowen R (1971) Periodic points and measures for axiom A diffeomorphisms. *Trans Am Math Soc* 154:377–397
- Brockett RW (1970) Finite dimensional linear systems. SIAM, Philadelphia
- Bullo F (2022) Lectures on network systems. Kindle Direct Publishing
- Colonius F (2012) Minimal bit rates and entropy for exponential stabilization. *SIAM J Control Optim* 50(5):2988–3010
- Colonius F, Kawan C (2009) Invariance entropy for control systems. *SIAM J Control Optim* 48(3):1701–1721
- Colonius F, Kawan C, Nair GN (2013) A note on topological feedback entropy and invariance entropy. *Syst Control Lett* 62(5):377–381
- Desoer CA, Vidyasagar M (2009) Feedback systems: input–output properties. SIAM, Philadelphia
- Dinaburg EI (1970) The relation between topological entropy and metric entropy. *Dokl Akad Nauk SSSR* 190(1):19–22 (**In Russian**)
- Hespanha JP, Ortega A, Vasudevan L (2002) Towards the control of linear systems with minimum bit-rate. In: 15th International symposium on mathematical theory of networks and systems, Notre Dame, IN, USA
- Hofbauer J, Sigmund K (1998) Evolutionary games and population dynamics. Cambridge University Press, Cambridge
- Katok A, Hasselblatt B (1995) Introduction to the modern theory of dynamical systems. Cambridge University Press, Cambridge

19. Kawan C, Delvenne JC (2016) Network entropy and data rates required for networked control. *IEEE Trans Control Netw Syst* 3(1):57–66
20. Kawan C, Latushkin Y (2016) Some results on the entropy of non-autonomous dynamical systems. *Dyn Syst* 31(3):251–279
21. Kolmogorov AN (1958) A new metric invariant of transitive dynamical systems and automorphisms of Lebesgue spaces. *Dokl Akad Nauk SSSR* 119(5):861–864 (**In Russian**)
22. Kolyada S, Snoha L (1996) Topological entropy of nonautonomous dynamical systems. *Random Comput Dyn* 4(2–3):205–233
23. Liberzon D (2003) *Switching in systems and control*. Birkhäuser, Boston
24. Liberzon D (2012) *Calculus of variations and optimal control theory*. Princeton University Press, Princeton
25. Liberzon D (2014) Finite data-rate feedback stabilization of switched and hybrid linear systems. *Automatica* 50(2):409–420
26. Liberzon D (2021) On topological entropy of interconnected nonlinear systems. *IEEE Control Syst Lett* 5(6):2210–2214
27. Liberzon D, Hespanha JP (2005) Stabilization of nonlinear systems with limited information feedback. *IEEE Trans Autom Control* 50(6):910–915
28. Liberzon D, Mitra S (2018) Entropy and minimal bit rates for state estimation and model detection. *IEEE Trans Autom Control* 63(10):3330–3344
29. Liu T, Jiang ZP, Hill DJ (2018) *Nonlinear control of dynamic networks*. CRC Press, Boca Raton
30. Lu W, di Bernardo M (2016) Contraction and incremental stability of switched Carathéodory systems using multiple norms. *Automatica* 70:1–8
31. Mancilla-Aguilar JL (2000) A condition for the stability of switched nonlinear systems. *IEEE Trans Autom Control* 45(11):2077–2079
32. Matveev AS, Pogromsky AY (2016) Observation of nonlinear systems via finite capacity channels: constructive data rate limits. *Automatica* 70:217–229
33. Matveev AS, Proskurnikov AV, Pogromsky A et al (2019) Comprehending complexity: data-rate constraints in large-scale networks. *IEEE Trans Autom Control* 64(10):4252–4259
34. Nair GN, Evans RJ (2003) Exponential stabilisability of finite-dimensional linear systems with limited data rates. *Automatica* 39(4):585–593
35. Nair GN, Evans RJ, Mareels IMY et al (2004) Topological feedback entropy and nonlinear stabilization. *IEEE Trans Autom Control* 49(9):1585–1597
36. Russo G, di Bernardo M, Sontag ED (2013) A contraction approach to the hierarchical analysis and design of networked systems. *IEEE Trans Autom Control* 58(5):1328–1331
37. Savkin AV (2006) Analysis and synthesis of networked control systems: topological entropy, observability, robustness and optimal control. *Automatica* 42(1):51–62
38. Shorten R, Wirth FR, Mason O et al (2007) Stability criteria for switched and hybrid systems. *SIAM Rev* 49(4):545–592
39. Sibai H, Mitra S (2017) Optimal data rate for state estimation of switched nonlinear systems. In: 20th International conference on hybrid systems: computation and control, Pittsburgh, PA, USA, pp 71–80
40. Sontag ED (2010) Contractive systems with inputs. In: Willems JC, Hara S, Ohta Y, et al (eds) *Perspectives in mathematical system theory, control, and signal processing*. Springer, Berlin, pp 217–228
41. Tatikonda S, Mitter S (2004) Control under communication constraints. *IEEE Trans Autom Control* 49(7):1056–1068
42. Tomar MS, Zamani M (2020) Compositional quantification of invariance feedback entropy for networks of uncertain control systems. *IEEE Control Syst Lett* 4(4):827–832
43. Vicinans GS, Liberzon D (2019) Estimation entropy for regular linear switched systems. In: 58th IEEE conference on decision control, Nice, France, pp 5754–5759
44. Vidyasagar M (2002) *Nonlinear systems analysis*, 2nd edn. SIAM, Philadelphia
45. Vu L, Liberzon D (2005) Common Lyapunov functions for families of commuting nonlinear systems. *Syst Control Lett* 54(5):405–416
46. Yang G, Liberzon D (2015) A Lyapunov-based small-gain theorem for interconnected switched systems. *Syst Control Lett* 78:47–54
47. Yang G, Liberzon D (2018) Feedback stabilization of switched linear systems with unknown disturbances under data-rate constraints. *IEEE Trans Autom Control* 63(7):2107–2122

48. Yang G, Schmidt AJ, Liberzon D (2018) On topological entropy of switched linear systems with diagonal, triangular, and general matrices. In: 57th IEEE conference on decision control, Miami Beach, FL, USA, pp 5682–5687
49. Yang G, Hespanha JP, Liberzon D (2019) On topological entropy and stability of switched linear systems. In: 22nd ACM International conference on hybrid systems: computation control, Montreal, Canada, pp 119–127
50. Yang G, Schmidt AJ, Liberzon D et al (2020) Topological entropy of switched linear systems: general matrices and matrices with commutation relations. *Math Control Signals Syst* 32(3):411–453
51. Yang G, Liberzon D, Hespanha JP (2021) Topological entropy of switched nonlinear systems. In: 24th ACM international conference on hybrid systems: computation and control, Nashville, TN, USA
52. Yang G, Liberzon D, Hespanha JP (2023) Topological entropy of switched nonlinear and interconnected systems. Technical report, Rutgers University. Available at <https://guosong-yang.github.io/publications>

**Publisher's Note** Springer Nature remains neutral with regard to jurisdictional claims in published maps and institutional affiliations.

Springer Nature or its licensor (e.g. a society or other partner) holds exclusive rights to this article under a publishing agreement with the author(s) or other rightsholder(s); author self-archiving of the accepted manuscript version of this article is solely governed by the terms of such publishing agreement and applicable law.